An Internal ALD-Based High Voltage Divider and Signal Circuit for MCP-based Photodetectors

Bernhard Adams^b, Andrey Elagin^a, Jeffrey W. Elam^b, Henry J. Frisch^a,
Jean-Francois Genat^{a,1}, Joseph S. Gregar^b, Anil U. Mane^b, Michael J. Minot^c,
Richard Northrop^a, Razib Obaid^{a,2}, Eric Oberla^a, Alexander Vostrikov^a,
Matthew Wetstein^a

^a*Enrico Fermi Institute, University of Chicago*

^b*Argonne National Laboratory*

^c*Minotech Engineering, Inc and Incom, Inc*

Abstract

We describe a pin-less design for the high voltage (HV) resistive divider of the all-glass LAPPDTM 8"-square thin photodetector module. The divider, which distributes high voltage applied to the photocathode to the two micro-channel plates (MCP's) that constitute the amplification stage, is comprised of the two MCP's and three glass mechanical spacers, each of which is coated with a resistive layer using Atomic Layer Deposition (ALD). The three glass grid spacers and the two MCP's form a continuous resistive path between cathode and anode, with the voltages across the MCP's and the spacers determined by the resistance of each. High voltage is applied on an external tab on the top glass window that connects to the photocathode through the metal seal. The DC ground is supplied by microstrips on the bottom glass plate that form the high-bandwidth anode. The microstrips exit the package through the glass-frit seal of the anode base-plate and the package sidewall. The divider is thus completely internal, with no HV pins penetrating the low-profile flat glass package. Measurements of the performance of the divider are presented for the 8"-square MCP and spacer package in a custom test fixture and for an assembled externally-pumped LAPPDTM prototype with an aluminum photocathode.

¹Present address, Universits Pierre et Marie Curie; Paris France

²Present address, Physics Dept., Univ. of Conn., Storrs, CT 06269

11	Contents	
12	1 Introduction	3
13	2 The HV Resistive Distribution Chain	6
14	2.1 Resistive Components	6
15	2.2 DC Current Path	8
16	2.3 The Signal Path for Fast-Risetime Pulses	10
17	2.3.1 Normal Anode Configuration	11
18	2.3.2 The ‘Inside-Out’ Anode	12
19	3 Implementation in the LAPPDTM Package	13
20	3.1 Mechanical Dimensions	14
21	4 Performance of the HV Divider	15
22	4.1 Test Facilities	16
23	4.1.1 The Spacer Station (ISS)	17
24	4.1.2 The Demountable Tile	18
25	4.2 Current-vs-Voltage (I-V) Curves	18
26	4.3 Thermal Coefficient	18
27	4.4 Pressure Dependence	19
28	4.5 Long-term Stability	20
29	5 Conclusions	21
30	6 Acknowledgments	23

31 1. Introduction

32 The LAPPD Collaboration [1] was formed to develop large-area photodetec-
33 tors based on micro-channel plates [2] for precise time-of-flight measurements
34 in large-scale detectors for High Energy Physics. In a number of applications
35 the ability to detect the arrival of multiple photons in a large-area plane, each
36 measured with a time resolution measured in pico-seconds ($1 \text{ psec} = 10^{-12} \text{ sec}$)
37 and a space resolution measured in millimeters, enables a 3D pattern recon-
38 struction using the 2D position of arrival of each photon and the transit time
39 to determine the remaining orthogonal 3rd component [3]. Additionally, a psec-
40 level measurement of the time coordinate allows a qualitative change in the
41 photodetector area needed to provide a given level of coverage for large diffuse
42 sources such as the large water-Cherenkov or scintillation counters used in par-
43 ticle and nuclear physics, as the addition of the transit drift time of the photon
44 transforms a 2-dimensional phase space into a much larger 3-dimensional space.
45 Optical systems can take advantage of measuring both the position and the time
46 of arrival to minimize expensive photocathode area while still preserving space
47 resolution³.

48 The amplification in conventional discrete-dynode photomultipliers (PMT's)
49 and microchannel-based photomultipliers (MCP-PMT's) is done by electron
50 multiplication, with the electrons accelerated between collisions with a dyn-
51 ode (in a PMT) or the wall of a capillary channel (in an MCP-PMT) to provide
52 energy for secondary electron emission. The multiplication is consequently ex-
53 ponential, and depends on the secondary-emission yield (SEY) of each collision
54 and the number of collisions (equal to the number of dynodes in a PMT). The
55 SEY in turns depends on the accelerating voltage between collisions, which in
56 a PMT is typically set by a resistive voltage divider that supplies each dynode
57 from a high voltage (HV) source at the input to the divider. The principle is the

³One can think of this as similar to rotations between transverse and longitudinal emit-
tances in accelerators.

58 same in an MCP-PMT, but rather than a divider made of discrete resistive ele-
 59 ments, the voltages between collisions are set by a DC current flowing through a
 60 resistive layer on the walls of the capillaries. In an MCP-PMT with the typical
 61 pair of capillary plates as an amplification section, voltage is usually applied
 62 to the top and bottom of each plate by deposition of a conducting electrode
 63 surface.

64 The LAPPDTM (Large Area Picosecond Photodetector) is an MCP-based
 65 photodetector, capable of imaging at high spatial and temporal resolution, in an
 66 ultra-high vacuum (UHV) hermetic package with an active area of 400 square
 67 centimeters. The modular detector design is based on a hermetic all-glass vac-
 68 uum tube package consisting of a thin window on which a bialkali photocathode
 69 has been deposited, two 8"-square micro-channel plates (MCP), and an anode
 70 implemented as high-bandwidth RF silver micro-striplines [4]. Amplification is
 71 provided by a pair of micro-channel glass substrates [5] coated by Atomic Layer
 72 Deposition (ALD) [6], with typical gains of more than 10^7 .

73 The HV distribution for the LAPPDTM can be implemented in a number of
 74 ways, depending on the application and possibly also on parameters of the pro-
 75 duction process. In the design described here, the HV distribution and the high
 76 frequency signal path are both integral parts of an economical mechanical struc-
 77 ture. The hermetic package has only 8 parts, all made of commonly-available
 78 sheet glass. The only additional element is a simple getter assembly formed
 79 from a strip of getter material and glass bead supports that is situated around
 80 the circumference of the channel plate stack assembly. An attractive feature
 81 for robustness and fabrication yield is there are no pins penetrating the pack-
 82 age; both the HV and the anode signals are brought in through metal layers
 83 deposited on the glass prior to assembly. The planar anode signal plane has an
 84 analog bandwidth of 1.6 GHz (3 db loss) [4] in this implementation.

85 The organization of the paper is as follows. Section 2 describes the resistive
 86 HV distribution chain, with the resistive elements and DC current path de-
 87 scribed in Sections 2.1 and 2.2, respectively. The high-speed (radio-frequency,
 88 RF) signal circuit, which is electrically and mechanically integrated with the

89 HV circuit, is discussed in Section 2.3 for the usual configuration with the an-
 90 ode pattern on the inside surface of the vacuum volume (Section 2.3.1), and a
 91 capacitively-coupled configuration with pads or microstrips on the outside sur-
 92 face (Section 2.3.2). The integration of the HV divider into the LAPPDTM her-
 93 metic package is described in Section 3, where the physical dimensions, ALD
 94 coating parameters, and electrical values are also summarized.

95 Measurements of the performance of the HV divider are presented in Sec-
 96 tion 4. A summary of the test facilities for the HV chain is given in Sec-
 97 tion 4.1. Section 4.1.1 describes a custom test facility, the Spacer Station (ISS),
 98 used to make DC measurements of current and voltage. A second test facility,
 99 the ‘Demountable Tile’, consisting of an LAPPDTM glass-body tile mechanical
 100 assembly, but with an O-ring window seal and a permanent connection to a
 101 vacuum pump rather than being a hermetically sealed tube, is used to make
 102 measurements of fast pulses, including time and space resolutions, as described
 103 in Section 4.1.2. Measurements of I-V curves and the dependence of the divider
 104 resistance on temperature, pressure, and time are presented in Sections 4.2-4.5.
 105 The paper concludes with a summary in Section 5.

Figure 1: The mechanical construction of the LAPPDTM module. All components are glass. The hermetic volume is formed by the top window (1), the side-wall (5), and the bottom plate (7). The photocathode is deposited on the inside of the window, and makes contact with the external HV input through a metalized border (4). The grid spacers (2) and the MCP's (3) are coated with ALD. The bottom plate (7) has silk-screened silver anode 50Ω microstrips fired on its surface (6) that penetrate a frit seal under the sidewall and connect to the digitizing electronics.

2. The HV Resistive Distribution Chain

The hermetic package, made of readily-available borosilicate glass [7], consists of a top window, sidewall, and anode bottom plate. The sidewall is hermetically sealed to the anode plate with glass frit to form a robust base unit. The top window is sealed with indium to the base in vacuum after the photocathode is deposited. HV is applied outside the vacuum volume on a window tab that makes contact with the metalized border of the window and the photocathode. Resistive grid spacers coated by ALD support the pressure on the top window and bottom anode plate. The three spacers and the two MCP plates, together with the (DC) grounded anode plane, form the resistive HV divider that determines the voltages across the MCP's and the three gaps. The silver anode strips [8] extend beyond the sidewall bottom seal to complete the electrical circuits for both signals and DC current. Atmospheric pressure transmitted through the top window and bottom anode plane compresses the 'stack' of grid spacers and microchannel plates into a rigid thin package.

A diagram of the layers of the HV divider is shown in Figure 1.

2.1. Resistive Components

Amplification in the tile is provided by a pair of microchannel-plates with $20\text{ }\mu\text{m}$ -diameter pores, arranged in a chevron configuration. The pores have a length-to-diameter ratio (L/D) of 60, making the thickness of each plate 1.2 mm. The plates are coated with a resistive layer by ALD with a target resistance of between 10 and 40 M Ω [9]. The plates are chosen within a pair to be matched in resistance within $\pm 10\%$.

To provide structural rigidity and the ability to support atmospheric pressure on the top and bottom of the package, the gaps in the vacuum volume from the cathode to the first MCP, from the first to the second MCP, and from the second MCP to the anode, are formed by spacers consisting of thin flat glass grids. The HV resistive divider chain is completed by coating the grid spacers with a resistive layer, also by ALD, as shown in Fig. 2.

Figure 2: The equivalent electrical circuit of the tile assembly. The upper diagram shows the DC circuit. The HV voltage divider is implemented by resistive ALD coatings of the grid spacers and the MCP's. (see Figure 1).

135 The parameters of the layers that make up the tile are given in Table 1 [10].
 136 A 2-mm grid spacer, shown in Figure 4, sets the height and voltage across the
 137 photocathode-MCP gap and the gap between the two MCP's. A 6.5-mm grid
 138 spacer similarly sets the height and voltage across the gap between the bottom of
 139 the second MCP and the anode plane. The grid spacers are aligned to minimize
 140 the occluded area and to transfer the force of atmospheric pressure in columnar
 141 fashion between the top and bottom plates.

142 A 2.3 cm by 0.076 cm cut-away indentation in each crossbar in one direction
 143 in the bottom spacer allows the vacuum volumes defined by the spacer grid to
 144 communicate with each other for pumping, as shown in Figure 3.

145 We have made tests with a Nichrome coating on the grid spacers and without.
 146 Because the MCP's are metalized with Nichrome top and bottom there is no
 147 need to metalize the grid spacers at those interfaces. However metalization of
 148 the top surface of the top spacer can provide a convenient method of distributing
 149 HV and current across the face of the (resistive) photocathode. The silver anode
 150 microstrips distribute the DC ground potential under the bottom spacer, which
 151 cannot be metalized without shorting the strips.

152 *2.2. DC Current Path*

153 The DC electrical circuit of the photodetector is shown in Figure 2. High
154 voltage is applied to a Nichrome border on the underside of the window via a
155 tab that extends beyond the sidewall. The Nichrome makes contact with the
156 top grid spacer to supply current to the resistive divider through the spacers
157 and MCP's.

158 Figure 5 shows the window, including the external tabs and Nichrome bor-
159 der that supply the input HV to the photocathode and the divider. The HV
160 is applied to the underside of two of the tabs, and connects to the cathode
161 through the metalization for the seal. The four metalized lines that extend into
162 the cathode provide HV distribution to the cathode plane, complementing the
163 distribution from the top spacer.

164 The internal five layers, consisting of three grid spacers and two MCP's, form

Figure 3: A partial assembly showing the ‘bottom’ spacer grid, the getter strip and its supporting glass beads, and the sidewall as they would be in the assembled tile base. The 2.3 cm by 0.076 indentations that allow the separate vacuum volumes in the tile to communicate with each other are visible as channels running from left to right on the top edges of the spacer.

Layer	Thickness	Material	Resistive Coating	Metalization (side)
Window	2.75 mm	B33	Photocathode (bottom)	Nichrome border (bottom)
Grid Spacer 1	2.0 mm	B33	ALD-GS	None
MCP 1	1.2 mm	Micropore	ALD-MCP	Nichrome (both)
Grid Spacer 2	2.0 mm	B33	ALD-GS	None
MCP 2	1.2 mm	Micropore	ALD-MCP	Nichrome (both)
Grid Spacer 3	6.5 mm	B33	ALD-GS	None
Anode	2.75 mm	B33	N/A	Silver strips (top)

Table 1: A tabulation of the layers in the tile assembly, starting with the top window and ending with the bottom anode layer. Mechanical stability against atmospheric pressure is provided by a glass grid spacer in each of the three gaps, as listed. All components except the microchannel plates are made from B33 borosilicate glass plate [7].

Figure 4: Two of the glass grid spacers after the resistive ALD coating has been applied. The grid spacers are cut from easily available B33 glass [7]. Mechanically, the spacers serve to transmit the compressive force of atmospheric pressure from the top to the bottom of the tube; electrically the resistive coating provides the voltage drop across each gap. Metalization of the top surface of the top spacer can serve to provide distribution of HV across the (resistive) photocathode.

165 a resistive voltage divider [11] that passes a nominal $100\ \mu\text{A}$ divider current from
 166 the cathode to the anode. Table 2 gives the nominal resistance and voltage drops
 167 across the divider.

168 The final step in the DC return path to HV ground is at each end of the
 169 anode microstrips, where individual $10\text{K}\Omega$ resistors terminate each strip to the
 170 copper substrate sheet that forms the signal ground-plane of the microstrips
 171 and the HV DC return, as shown in Fig. 2.

172 *2.3. The Signal Path for Fast-Risetime Pulses*

173 The pulses from photons incident on the photocathode have sub-nsec rise-
 174 times, with typical bandwidths for the present 20-micron pores in the 1-2 GHz

Figure 5: The glass window, showing the Nichrome border that is the ‘tie layer’ supporting the indium seal to the glass sidewall. The external tabs and the metalized border also supply the input HV to the cathode and resistive divider. The view is from the air-side (top); the Nichrome metalization for the seal and the HV distribution is visible on the vacuum-side (underneath) along the perimeter and on the four lands extending into the interior of the cathode.

Layer	Resistance	Voltage Drop
Grid Spacer 1	2 M Ω	200 V
MCP 1	10 M Ω	1000 V
Grid Spacer 2	2 M Ω	200 V
MCP 2	10 M Ω	1000 V
Grid Spacer 3	6.5 M Ω	650 V
Total	28.5 M Ω	3050 V

Table 2: The target resistances and nominal voltage drops in the internal HV divider. The divider current is set at 100 μ A, corresponding to a limit of approximately 1 μ A of current draw from signal pulses [11].

range. The DC HV path and the path of the fast signal pulses share the same HV distribution and ground. For the signal path, however, there are two configurations we have considered, a ‘normal’ one in which the charge of the fast signals is collected and recorded from the anode microstrips inside the vacuum volume, and an ‘inside-out’ geometry in which the anode is a thin metal layer that serves as a DC ground, but is thin enough so that the fast signal pulses capacitively couple through to strips or pads on the external side of the bottom plate. These are described in turn below.

2.3.1. Normal Anode Configuration

The signal path maintains the 50 Ω impedance of the strip onto the printed circuit card containing the waveform sampling 6-channel PSEC4 ASICs [12] that digitize the signals. The thickness of the anode glass plate and the width of the strips determine the impedance of the microstrip lines [4, 13]. While the choice of impedance depends on a number of considerations, we chose a 50 Ω impedance for convenience in testing to match cabling and oscilloscope impedances. The choice of the anode plate thickness is application specific, with impedance, strip parameters, occupancy, weight, cost, amount of inactive material in the path of charged particles being some of the considerations. After the plate thickness is chosen the width of the anode strips can be set so to

194 determine the characteristic impedance. A further parameter is the gap between
195 strips, which is vulnerable to charging in high-rate applications if electric field
196 lines terminate on the dielectric.

197 Each 50Ω stripline is impedance-matched to the PC cards that digitize the
198 signals and that mate with the edge of the end tiles of a tile row, as shown in
199 Fig. 6. The DC return for the divider current through the $10K\Omega$ resistor has
200 a much higher impedance than the 50Ω signal path. For flexibility in testing,
201 an easily removable connection was made using low profile Electro-Magnetic
202 Interference (EMI) shielding gaskets [14]. Each EMI gasket strip was cut at
203 the pitch interval into separate RF fingers and mounted on a $1/2''$ G10 bar to
204 match the anode spacing. Figure 6 shows the connections between the strips on
205 the tile and the strips on the PC card used for testing the tiles.

206 2.3.2. The ‘Inside-Out’ Anode

207 There are a number of applications, such as large collider detectors in HEP
208 and some medical imaging cameras, that would have many particles arriving in a
209 narrow time window and consequently high occupancies in a strip-line readout.
210 These applications would benefit from a 2-dimensional ‘pad’ readout rather than
211 a 1-dimensional stripline geometry.

212 The fast risetime of the signal pulses from the MCP amplification chain
213 provides a mechanism to extract the signals from the vacuum volume by ca-
214 pacitively coupling through the glass anode bottom plane. In this ‘inside-out’
215 implementation, a uniform metal layer thinner than a skin-depth at frequencies
216 characteristic of the MCP risetime is deposited on the inner (vacuum-side) side
217 of the anode bottom glass plate, replacing the microstrips. This layer provides
218 the ground return for the DC HV current. The outer (air-side) side of the anode
219 plate supports the readout pattern deposited by metalization, typically in pads
220 or strips. This layer can then be connected to the electronics and additional
221 grounds as necessary.

222 3. Implementation in the LAPPDTM Package

223 The LAPPDTM design integrates the mechanical structure with both the
224 high frequency signal path and the HV DC current path into a single economical

Figure 6: A picture showing the interface between the tile anodes and the readout system at the end of a row of tiles. The DC path to HV ground at the end of the microstrips is through individual $10\text{K}\Omega$ resistors on each strip to HV ground on the analog card that holds the waveform sampling ASICs. To allow easy disconnection for testing, a bar of FR4 with RF-fingers is used to bridge the gap between each of the 30 strips on the tile to the corresponding strip on the PC card.

225 structure. The advantage of the integrated design is the construction is planar,
 226 with all electrical connections lying in the same plane as the thin form-factor
 227 detector module itself. This allows a ‘tiling’ of large areas with a higher filling
 228 factor than would be possible with individual modules with edge-readout. We
 229 give details of the implementation below.

230 *3.1. Mechanical Dimensions*

231 The tile assembly is a flat glass package with transverse dimensions of 229.1
 232 mm in the strip direction by 220 mm transverse. The active area is 203 mm
 233 by 203 mm (8" by 8"). The current prototype grid spacers occlude 16% of the
 234 active area; this will be reduced in future designs after more experience with
 235 this first-generation simple implementation.

236 A mockup of an assembled glass module, made with prototype glass parts
 237 but without a photocathode or vacuum seal, is shown in Figure 7. Multi-
 238 ple modules can be integrated into a ‘supermodule’, sharing the RF-strip-line
 239 readout mounted on the ‘Tray’ that also supports the electronics, as shown in
 240 Figure 8 [4].

241 The tile is made from glass layers stacked to form a rigid structure when
 242 compressed by atmospheric pressure. The vacuum volume is enclosed by the
 243 2.75 mm-thick top window, a standard plate glass thickness. The photocathode
 244 is on the bottom surface of the window, facing the top of the upper MCP (see
 245 Fig. 1). The anode plate with silver microstrips on its top surface, serves as the
 246 bottom of the vacuum volume, and is also 2.75 mm-thick. A rectangular border
 247 of 5.08 mm (0.200") width, cut from a standard thickness glass plate, forms the
 248 sidewall of the volume.

249 The sidewall is sealed to the anode plate over the microstrips with a glass
 250 frit seal. The metal microstrips extend beyond the sidewall so that contact can
 251 be made with neighboring tiles [4] or the digitization printed circuit cards at
 252 the end of a tile-row [12].

Figure 7: An 8"-square (20 cm-by-20 cm) LAPPD™ module ('tile'). The tiles are hermetically sealed vacuum tubes that provide the photocathode and MCP-based amplification chain. The upper layer of the micro-strip RF transmission lines that form the anode are on the internal surface of the bottom plate of the tile; the ground plane of the transmission line is the upper surface of the supporting 'Tray', shown in Figure 8. The thin format and modular nature of the photodetector allow application-specific optimization.

253 4. Performance of the HV Divider

254 The proposal to use ALD coatings on the grid spacers and MCP's to deter-
 255 mine the amplification and transport voltages had unknown risks at the outset
 256 of the LAPPD program. In particular we are relying on the stability of the
 257 coatings under a large mechanical pressure. Atmospheric pressure corresponds
 258 to almost 1200 lbs on the top and bottom plates. The pressure on the MCP
 259 surfaces is magnified by the ratio of areas of the grid spacer to the total area,
 260 approximately a factor of 10. The surfaces of the MCP's consist of glass capil-
 261 laries with $\sim 65\%$ open area, and have both metal electrode material and ALD
 262 secondary-emitting material; the surfaces of the grid spacers have a grid-specific
 263 ALD resistive coating. How these interfaces behave under pressure, with tem-

Figure 8: A ‘supermodule’ consisting of twelve 8”-square LAPPDTM modules (‘tiles’) mounted on a ‘tray’ that provides the ground plane for the anode micro-strips and the support for the digitizing electronics at each end. Each row of 4 tiles shares the same anode strips in series, as described in Ref. [4].

264 perature, and over time is not tractable to calculation; we have consequently
 265 embarked on a series of measurements of the stability of the HV divider assem-
 266 bly under HV and pressure. Several of the test facilities are described in turn
 267 below.

268 *4.1. Test Facilities*

269 Section 4.1.1 describes a custom test facility, the Spacer Station (ISS) used
 270 to make DC measurements of current and voltage. A second test facility, the
 271 ‘Demountable Tile’, consisting of an actively-pumped glass-body tile mechanical
 272 assembly with an O-ring top seal, is used to make measurements of fast pulses
 273 at resolutions down to 5 psec, as described in Section 4.1.2.

Figure 9: The spacer station (ISS) used to measure resistances of individual grid spacers, MCP's, and the complete divider. A grid spacer is shown in the vacuum volume; the copper plate being held on the right is an electrode that supplies the HV to the piece being measured. A thin insulating layer separates the copper HV electrode from the 2.75-mm-thick top window, which is thin enough that atmospheric pressure deflects it until stopped by the internal stack of MCP's and grid spacers, compressing the divider.

274 4.1.1. The Spacer Station (ISS)

275 To measure the resistance of the grid spacers and MCP plates versus pres-
 276 sure, temperature, and over time, a simple flat square vacuum vessel with a
 277 flexible lid consisting of an aluminum foil incapable of withstanding atmospheric
 278 pressure was constructed. The window provides the same (atmospheric) pres-
 279 sure on the component stack as the glass window of the sealed tile. Figure 9
 280 shows the ISS open to air with a single grid spacer inside. The copper plate
 281 to the right of the ISS provides HV contact to the layers being measured; the
 282 ISS frame is the DC ground. Single, multiple, or a full stack of the component
 283 layers (grid spacer and MCP) can be measured using suitable non-conducting

284 spacers above the copper plate.

285 4.1.2. *The Demountable Tile*

286 In order to test the time and position response of the photodetectors as a
287 system we have constructed a facility [15] of which the key components are a
288 pulsed Ti:Sapphire laser with a pulse width ~ 100 fsec, and a data-acquisition
289 system with 60 channels of 10-15 GS/sec waveform sampling readout, shown
290 in Figure 10. The Demountable Tile is constructed with the anode frit-sealed
291 to the sidewall and the internal HV divider as in the LAPPDTM, but has
292 a removable window sealed with an O-ring so that MCP plates can be easily
293 inserted and removed for rapid testing. The tile consequently has to be actively
294 pumped, and has an air-stable aluminum cathode.

295 The HV control system for the Demountable Tile Test Facility allows for
296 measuring voltage and current under computer control [15], and similarly mea-
297 suring the stability of the gain and spatial response over the face of the tile [16].
298

299 4.2. *Current-vs-Voltage (I-V) Curves*

300 One concern about using ALD-coated elements as a HV divider is the possi-
301 ble non-linear or non-reproducible behavior as a function of voltage. Figure 11
302 shows the measured I-V curve using the ISS facility. The behavior is linear, and
303 demonstrates little hysteresis.

304 4.3. *Thermal Coefficient*

305 The temperature dependence of the divider resistance is of concern due to
306 the vulnerability of MCP-based photodetectors to thermal run-away [17]. The
307 divider resistance depends on the thermal coefficients of the ALD-coatings of
308 the grid-spacers and MCP's. The resistivity of the coatings on the grid spacers
309 is different from that for the MCP's, as the effective conducting areas are so
310 different. At present the three grid spacers are coated in the same batch, so the
311 difference in resistance is determined solely by the difference in the conduction

Figure 10: The Demountable Tile test setup, consisting of glass tile of the LAPPDTM design constructed with the LAPPDTM hermetic package and internal divider, but with a removable window sealed with an O-ring. The tile consequently has to be actively pumped, and, as a bialkali anode cannot survive in air, has an aluminum cathode. However the HV divider and signal circuit are the same as in the sealed tile. The tile is shown sitting on a 4-tile anode readout ‘Tray’, which is equipped with 60 channels (30 strips on each end) of 10-15 GS/sec waveform sampling PSEC-4 ASICs.

312 path length of the thicker grid spacer from that of the other two (see Table 1).
 313 Figure 12 shows the resistance of the HV divider as a function of temperature,
 314 measured in the ISS.

315 4.4. Pressure Dependence

316 The contacts between the grid spacers and the MCP’s are complex electri-
 317 cally and mechanically [18]. The Spacer Station (ISS) was constructed with

Figure 11: The current-vs-voltage (I-V) data for the ALD-based HV divider, as measured in the ISS test facility. The voltage is measured both ramping up and ramping down increased (red, squares) vs decreased (blue, circles). The slope gives the effective resistance of the multi-layer divider.

318 a thin foil top ‘window’ specifically to measure the contact resistances versus
 319 pressure. The pressure is varied by control of the vacuum inside the ISS through
 320 a needle valve to the pump. A curve of resistance vs the pressure on the layers
 321 of the HV divider (lbs/in²) is shown in Figure 13. The drop in resistance of
 322 approximately 20% at low pressure is presumably due to changes in contact. A
 323 small amount of hysteresis is observed; however in an operating evacuated tile
 324 the pressure on the stack is stable, with only minor variations due to changes
 325 in atmospheric pressure or temperature.

326 4.5. Long-term Stability

327 The large pressure (> 1000 lbs) on the HV divider transmitted through the
 328 thin glass top window and bottom plate is also cause for concern about the
 329 long-term stability of the electrical contacts between the layers that constitute
 330 the divider. The mechanical and electrical stability of the interface are subject
 331 to changes due to pressure, electro-chemistry, and temperature, as well as a

possible slow creep of a component or layer under the pressure. Over the course of 11 months under vacuum, a stack of two MCP's and 3 grid spacers the Demountable Tile has remained stable in resistance, gain, and uniformity, giving us confidence in the mechanical design.

5. Conclusions

The use of ALD for functionalizing glass capillaries and glass grid spacers enables a modular compact design of a thin planar photodetector with an internal HV divider. The LAPPDTM module is simple, consisting of eight parts, all made of glass, and a simple getter assembly. The amplification section consists of two 203 mm-by-203 mm MCP's. The HV divider is formed by applying resistive coatings to the grid spacer in each of the three gaps: between the photocathode and MCP1, between MCP1 and MCP2, and between MCP2 and the anode microstrip transmission lines.

Figure 12: The resistance of the HV divider as a function of temperature. The measurements between room temperature and the temperature of ice were measured by necessity ‘on the fly’, rather than in thermal equilibrium, a possible explanation of the apparent offset from the curve.

345 The sealed module sits flat on a ground plane that is shared with neighboring
 346 modules; there are no connecting pins on the back side. The HV is applied to an
 347 external metalized tab that connects to the metal top seal between the window
 348 and the glass sidewall. The DC ground is provided by the anode ground plane
 349 of microstrips, which are deposited on the top surface of the glass bottom plate
 350 of the hermetic package, and extend through the seal to outside the vacuum
 351 volume. The anode microstrips can be connected in series to form a continuous
 352 anode up to 90 cm long, with the DC ground return and ASIC readout on the
 353 ends of the outer-most modules [4].

354 Measurements of current vs voltage in the HV divider have been made in
 355 a custom test setup and in the module glass body on a 90-cm anode. The
 356 measurements in the test setup have been made as a function of the pressure on
 357 the divider, controlled by varying the vacuum in the module. Measurements of

Figure 13: The resistance of the HV divider as a function of the pressure compressing the divider stack. The pressure is varied by using the differential between atmospheric pressure on one side of the thin foil window at the top of the ISS and the partial vacuum inside the volume. The pressure in the ISS is controlled by pumping through a needle valve. Note the suppressed zero on the ordinate.

the temperature dependence and stability are also presented. An 11-month test under vacuum gives us confidence in the long-term stability of this relatively simple integrated electro-mechanical design.

6. Acknowledgments

We thank our colleagues in the Large Area Psec Photodetector (LAPPD) Collaboration for their contributions and support. Special thanks are due to A. O'Mahony (Incom) and Neal Sullivan (Arradance) for their essential work on ALD coatings for the components of the internal stack. Thanks are due to R. G. Wagner (ANL) for technical support; D. Walters, and J. Williams (ANL) for metalization of the windows and vacuum expertise; and H. Wen and H. Gibson (ANL) for laser and electronics support at the APS testing lab. We are deeply grateful to E. Hahn (Fermilab) for meticulous metalization of the MCP's, and P. Murat (Fermilab) for support. R. Metz (UC) provided expert machining of test setups and glass parts. M. Heintz (UC) supplied crucial technical and computer systems support. We thank Q. Guo (UC), Chian Liu (ANL) and H. Clausing (H. Clausing, Inc) for expert advice and large amounts of time teaching us about cleaning and metalization of glass. We also thank our superb glass vendors P. Jaynes (CatI Glass, Inc) and P. Seegebrecht (Webcorr) for metalization and glass

The activities at Argonne National Laboratory were supported by the U. S. Department of Energy, Office of Science, Office of Basic Energy Sciences and Office of High Energy Physics under contract DE-AC02-06CH11357, and at the University of Chicago by the Department of Energy under DE-SC-0008172, the National Science Foundation under grant PHY-1066014, and the Driskill Foundation.

- [1] The original LAPPD institutions include ANL, Arradance Inc., the Univ. of Chicago, Fermilab, the Univ. of Hawaii, Muons, Inc, SLAC, SSL/UCB, and Synkera Corporation. More detail can be found at <http://psec.uchicago.edu/>.
- [2] J.L. Wiza, Micro-channel Plate Detectors. Nucl. Instr. Meth. 162, p567; 1979
- [3] E. Oberla, Ph.D thesis, in preparation. We thank H. Nicholson for the original suggestion of using large-area planar detectors for water Cherenkov neutrino detectors, and for the OTPC name.
- [4] H. Grabas, R. Obaid, E. Oberla, H. Frisch, J-F. Genat, R. Northrop, F. Tang, D. McGinnis, B. Adams, M. Wetstein, *RF Strip-Line Anodes for Psec Large-Area MCP-based Photodetectors*. Nucl. Instr. Meth. A71, p124; 2013
- [5] The glass capillary substrates are produced by Incom Inc. Charlton Mass. See <http://www.incomusa.com/>.
- [6] S. M. George, *Atomic Layer Deposition: An Overview*; Chemical Reviews 2010, 110, (1), 111-131;
J. W. Elam, D. Routkevitch, and S. M. George, *Properties of ZnO/Al₂O₃ Alloy Films Grown Using Atomic Layer Deposition Techniques*; Journal of the Electrochemical Society 2003, 150, (6), G339-G347;
D. R. Beaulieu, D. Gorelikov, H. Klotzsch, P. de Rouffignac, K. Saadatmand, K. Stenton, N. Sullivan, and A. S. Tremsin, *Plastic microchannel plates with nano-engineered films*; Nucl. Instr. Meth. A633, S59-S61 (2011);
O.H.W. Siegmund, J.B. McPhate, S.R. Jelinsky, J.V. Vallerga, A.S. Tremsin, R. Hemphill, H.J. Frisch, R.G. Wagner, J. Elam, and A. Mane, *Development of Large Area Photon Counting Detectors Optimized for Cherenkov Light Imaging with High Temporal and sub-mm Spatial Resolution*; NSS/MIC 2011 IEEE, p2063 (Oct., 2011).
- [7] http://psec.uchicago.edu/glass/borofloat_33_e.pdf#page=28; The dielec-

411 tric constant is 4.6 and the loss tangent is 37×10^{-4} , both measured at
412 25C and 1 MHz.

413 [8] Ferro Corp., 251 Wylie Ave., Washington PA 15301. We are grateful to E.
414 Axtel for extensive assistance with selecting the silver ink for silk-screening
415 the anode microstrips.

416 [9] A. U. Mane, W. M. Tong, A. D. Brodie, M. A. McCord, and J. W. Elam,
417 *Atomic Layer Deposition of Nanostructured Tunable Resistance Coatings:*
418 *Growth, Characterization, and Electrical Properties*, ECS Transactions, 64
419 (9) 3-14 (2014);
420 A. U. Mane and J. W. Elam, *Atomic Layer Deposition of W:Al₂O₃*
421 *Nanocomposite Films with Tunable Resistivity*, Chem. Vap. Deposition, 19,
422 186-193, (2013)

423 [10] The tabulated values are those in current use. They can be changed to
424 optimize the voltages across the respective gaps for specific performance
425 goals. The total thickness depends on the height of the sidewall, which also
426 can be optimized for different applications.

427 [11] *Photomultiplier Tubes: Principles and Applications*, S-O Flyckt and C.
428 Marmonier; Photonis Brive, France, Sept. 2002

429 [12] E. Oberla, H. Grabas, J.-F. Genat, H. Frisch, K. Nishimura, G. S.
430 Varner, *A 15 GSa/s, 1.5 GHz Bandwidth Waveform Digitizing ASIC*,
431 Nucl.Instrum.Meth. A735 (2014) 452-461.

432 [13] For an excellent discussion of transmission lines, see E. Bogatin, *Signal*
433 *Integrity Simplified*, Prentice Hall Professional Technical Reference, 2004.
434 Chapter 10 is especially clear on cross-talk in striplines.

435 [14] Leader Tech part number 12-60LPAH-BD-16; Laird Technologies, Item 97-
436 115

437 [15] B. Adams, M. Chollet, A. Elagin, R. Obaid, E. Oberla, A. Vostrikov,
438 P.Webster, M. Wetstein; *A Test-Facility for Large-area Microchannel Plate*

- 439 *Detector Assemblies Using a Pulsed sub-Picosecond Laser*, Rev. Sci. Instrum. 84, 061301 (2013)
440
- 441 [16] B. Adams, A. Elagin, M. Wetstein et al.; *Measurements of the Gain, Time*
442 *Resolution, and Spatial Resolution of a 2020 cm² MCP-based Picosecond*
443 *Photo-detector*, Nucl. Instrum. Meth. A732 (2013)
- 444 [17] C. W. Carlson and J. P. McFadden *Design and Application of Imaging*
445 *Plasma Instruments*, in *Measurement Techniques in Space Plasmas: Particles*, R. F. Pfaff, J.E. Borovsky, and D. T. Young eds.; American Geophysical Union pub. (1998)
446
447
- 448 [18] The measurements presented here are made with MCP's that have the
449 electrode surface 'under' the ALD resistive and emissive coatings. The other
450 option, 'over', has the electrode on top of the ALD coatings. Both options
451 have their merits and drawbacks.