1 Development of a plasma panel radiation detector

2 R. Ball^a, J. R. Beene^b, M. Ben-Moshe^c, Y. Benhammou^c, R. Bensimon^c,
3 J. W. Chapman^a, E. Etzion^c, C. Ferretti^a, P. S. Friedman^d, D. S. Levin^a,
4 Y. Silver^c, R. L. Varner^b, C. Weaverdyck^a, R. Wetzel^a, B. Zhou^a,
5 T. Anderson^e, K. McKinny^e, E. H. Bentefour^f

6 ^a *University of Michigan, Department of Physics, Ann Arbor, Michigan, 48109, USA.*

7 ^b *Oak Ridge National Laboratory, Physics Division, Oak Ridge, Tennessee, 37831, USA.*

8 ^c *Tel Aviv University, Beverly and Raymond Sackler School of Physics and Astronomy,*
9 *Tel Aviv, Israel.*

10 ^d *Integrated Sensors, LLC, Ottawa Hills, Ohio, 43606, USA.*

11 ^e *GE Measurement and Control, Reuter-Stokes Product Line, Twinsburg, Ohio, 44087,*
12 *USA.*

13 ^f *Ion Beam Applications S. A., Louvain La Neuve, B-1348 Belgium.*

14 Abstract

15 This article reports on the development and experimental results of com-
16 mercial plasma display panels adapted for their potential use as micropattern
17 gas radiation detectors. The plasma panel sensor (PPS) design and materials
18 include glass substrates, metal electrodes and inert gas mixtures which pro-
19 vide a physically robust, hermetically-sealed device. Plasma display panels
20 used as detectors were tested with cosmic ray muons, beta rays and gamma
21 rays, protons, and thermal neutrons. The results demonstrated rise times
22 and time resolution of a few nanoseconds, as well as sub-millimeter spatial
23 resolution compatible with the pixel pitch.

Preprint submitted to Nuclear Instruments and Methods in Physics Research Section A June 11, 2014

24 1. Introduction

25 This article reports on the development and testing of commercial plasma
26 display panels adapted for use as a novel type of micropattern gas radiation
27 detector. Plasma display panels (PDP) are commonly used in televisions and
28 graphical display devices. Their design and production is supported by an
29 extensive and experienced industrial base with four decades of development.
30 The application of PDPs as particle detectors is referred to as a plasma panel
31 sensor (PPS) [1–6]. The primary motivation underlying the PPS concept is
32 to use well established manufacturing processes of PDPs to develop scalable,
33 inexpensive and hermetically sealed gaseous detectors with the potential for
34 a broad range of commercial and research applications.

35 A commercial PDP consists of millions of cells per square meter, each
36 of which can initiate and sustain a plasma discharge when addressed by a
37 bias-voltage signal [7]. A PDP, in the simplest matrix configuration, consists
38 of an envelope of two flat, parallel, glass plates with line electrodes deposited
39 on the internal surfaces. The plates are sealed together at the edges with the
40 top and bottom electrodes aligned perpendicularly. The gap separating the
41 two plates is between 200-400 μm and is filled with a Penning gas mixture
42 of mostly Xe, Ar or Ne, typically at pressures of about one-half atmosphere.
43 In such a structure, a pixel is made of an electrode intersection and gas gap.

44 A PPS incorporates the general structure of a PDP, but instead of actively
45 inducing a plasma discharge with an applied voltage delivered to an addressed
46 pixel, the plasma discharge is caused by ionizing radiation entering a PPS
47 cell biased with a constant DC voltage above the Paschen potential. Results
48 reported in this article were produced with commercial PDPs modified in
49 specific ways to allow them to be used as particle detectors. They operated
50 with DC bias voltages, had no dielectric barriers to isolate individual cells
51 and had no phosphors in the cells. These panels were a simple matrix of
52 anodes and cathodes with a gas filled gap of a few hundred micrometers. An
53 example of a test device is shown in Figure 1. The modifications made to
54 the panels were:

- 55 • Panels were normally fabricated with a hermetically sealed glass port.
56 This was replaced with a stainless steel valve assembly that connects
57 the panel to a gas mixing and vacuum pump system.
- 58 • The original Ne based panel gas was replaced with a test gas.

- The electrodes in the commercial panels were made from both Ni and SnO₂:F. A selection of the tested PPS panels used all Ni electrodes. The Ni was found to be much more resistant than the SnO₂:F to sputtering degradation.
- The electronics required for panel display operation was replaced with signal extraction circuitry on the readout anode electrodes.
- The high voltage bias was routed through quench resistors connected to each cathode electrode.

The above modifications allowed these commercial units to serve as a useful test bench for the PPS concept. The modified commercial panels served as prototypes for investigations and the results obtained from them have informed the next generation of PPS panels, the subject of a future paper. Commercial PDPs are sealed devices designed to work for 10⁵ hours. One panel filled with a Xe-based gas mixture at 600 Torr and hermetically sealed in 2003 produced signals when operated as a PPS seven years later, clearly demonstrating the long term stability of the materials and gas mixture.

Figure 1: A modified commercial PDP (type VPA in Table 1).

The panels evaluated in this report differed from each other in the electrode material, pixel density and size, and gas gap, that is separation of the anodes and cathodes. For the hit position studies, a type MP plasma panel was employed with a pixel pitch/granularity of 1.02 mm. For the investigation of panel timing, efficiency and response to various particle types a larger

80 VPA panel was used with a pixel pitch/granularity of 2.54 mm. The specifi-
81 cations of these two different types of panels are summarized in Table 1.

Table 1: *PDP manufacturer's specifications. The packing fraction is the ratio between the active pixel area and total area. The electrode length includes only the section inside the gas volume. HV=high voltage, RO=readout. The dielectric mesh defines the pixel perimeter but does not act as a barrier between pixels. The panel type name is an internal identifier without global significance.*

	Panel type VPA	Panel type MP
HV electrodes material	Ni	Ni
HV electrodes width (mm)	1.40	0.44
HV electrodes length(mm)	81	65
RO electrodes material	Ni	SnO ₂ :F
RO electrodes width (mm)	1.27	0.71
RO electrodes length(mm)	325	131
Electrodes pitch (mm)	2.54	1.02
Active pixel area (mm ²)	1.50	0.22
Packing fraction	23.5%	22.0%
Gas gap (mm)	0.38	0.29
Glass thickness (mm)	2.23	2.23
Electrodes thickness (mm)	0.02	0.02
Dielectric mesh thickness (mm)	0.02	0.02
VISHAY product number	PD-128G032-1	PD-128G064-1

82 Signals were investigated from panels filled with different gas mixtures
83 at various pressures, exposed to radiation from radioisotope sources, parti-
84 cle beams and cosmic rays. The various mixtures were either commercially
85 obtained or produced in our gas mixing system.

86 2. Operational principles

87 The use of PDPs as particle detectors requires that a charged particle
88 will generate enough ion-pairs to initiate an avalanche leading to a discharge.
89 This operational mode must be beyond the proportional region in the Geiger
90 region [8] of gas ionization to achieve the desired fast, high gain response.
91 This mode of operation of a cell can yield copious photons, photoelectrons
92 and metastable atoms which could, due to the lack of physical barrier between
93 the pixels, propagate and spread the discharge to other pixels.

94 Various mechanisms mitigate discharge regeneration in a PPS. Small
95 amounts of gases such as CO₂ or CF₄ are added to the primary gas to

96 absorb the photons through non-radiative vibrational and rotational exci-
 97 tations. Penning type mixtures [9] may also be used wherein the dopant
 98 gas has a first ionization energy level lower than the host gas excited states,
 99 e.g., CO_2 or CF_4 in Ar. The Penning transfer process allows for collisional
 100 de-excitation of the long-lived, metastable states. Finally, the discharge is
 101 externally quenched with a large resistor connected in series to each pixel or
 102 chain of pixels on the high voltage (HV) electrode. The pixels are then al-
 103 lowed to recover on a time scale determined by the RC time constant, where
 104 C is the effective pixel capacitance, effectively dominated by the choice of
 105 the quench resistor. This time constant should be commensurate with the
 106 time required for positive ions to neutralize and gas metastable species to
 107 decay [10].

108 The detailed mechanism for the discharge process is uncertain. A classic
 109 Townsend gas avalanche is limited by space charge buildup that negates the
 110 applied electric field, known as the Raether limit [11, 12]. The gas discharges
 111 that occurred in PPS pixels produced charge in excess of the Raether limit.
 112 This is shown in the next section where the signal is described by a simple
 113 capacitive discharge model. This model is valid after the discharge has fully
 114 evolved between the pixel electrodes. We do not yet have the complete
 115 description of the progression from avalanche to full discharge that is required
 116 to accurately predict the gas dependent signal evolution.

117 2.1. Signal model

118 An idealized model for one pixel in the PPS detector is shown in the equiv-
 119 alent circuit model in Figure 2, where R_q is the quench resistor ($\sim 100 \text{ M}\Omega$),
 120 C is the pixel total *effective* capacitance and R_t is the 50Ω termination re-
 121 sistor over which the signal is read.

Figure 2: Idealized schematic view of a single pixel.

122 The effective pixel capacitance includes the capacitance presented by the
 123 crossing of two orthogonal electrode lines and that from stray or parasitic
 124 couplings with all the other electrodes in the panel. This effective pixel capac-
 125 itance in a type VPA panel was modeled using the COMSOL [14] package
 126 which uses the finite element method to solve the Poisson equation. This
 127 three dimensional model simulates the entire volume of the detector and
 128 specifies the electrode dimensions, pitch, gap and number of electrodes in an
 129 orthogonal square array. The model did not account for the dielectric glass
 130 substrates, nor the thin dielectric mesh overlaid on the electrodes at the cell
 131 perimeter. The computation was run for a series of increasing array sizes up
 132 to 15×15 at which point further increases became computationally imprac-
 133 tical. The simulated capacitance versus number of pixels, shown in Figure 3,
 134 was fit and extrapolated to the VPA panel array size of $32 \text{ pixels} \times 128 \text{ pix-}$
 135 els . The extrapolated result was $1.9 \pm 0.15 \text{ pF}$, where the uncertainty was
 136 determined from the fit errors. By comparison, the effective capacitance was
 137 also measured with an Agilent 4263B LCR meter. A series of ten measure-
 138 ments were conducted for various pair combinations. The measured value
 139 was $2.7 \pm 1.0 \text{ pF}$, consistent with the computation while the capacitance of
 140 a single electrode pair was calculated to be almost an order of magnitude
 141 lower, at 0.35 pF .

142 An estimate of the amount of charge in a signal with an amplitude of
 143 several volts is given by: $V_{\text{signal}} = \frac{\Delta q}{\Delta t} R_t$ where V_{signal} is the measured signal
 144 amplitude, Δt is the pulse width and R_t is the 50Ω termination resistance.
 145 Average values for MP type panels (see Table 1) are $V_{\text{signal}} \approx 5 \text{ volts}$ and
 146 $\Delta t \sim 5 \text{ ns}$, yielding $\Delta q \sim 10^{-9} \text{ C}$, or about 10^{10} electrons. Alternatively,
 147 $\Delta q = C_{\text{pixel}} \cdot \Delta V_{HV}$ where ΔV_{HV} is the change in the bias voltage on one
 148 pixel during discharge. ΔV_{HV} is about 300 volts on top of a bias voltage of
 149 1000 volts. C_{pixel} is the effective capacitance of the pixel described above,
 150 yielding a similar estimate of the charge. This amount of charge greatly
 151 exceeds $\approx 10^8$ gain expected from the Raether limit [11, 12].

152 The signal characteristics were further described by a SPICE [16] model
 153 which simulated the electronic response of a single pixel embedded among
 154 neighbors, connected via direct and stray capacitances, inductances and line
 155 resistance. In this model the fundamental single pixel circuit included the
 156 capacitance of the cell, the self-inductance and resistivity of the lines, and the
 157 nearest neighbor parasitic coupling capacitances. Not included in the SPICE
 158 model were the readout electronics (printed circuit card, passive components,
 159 cables, etc). The input parameters were determined with a COMSOL-based

Figure 3: Computed capacitance versus the number of pixels. A fit (solid line) to the simulated data is extrapolated with uncertainties (dashed lines) to the number of pixels in a type VPA panel.

160 electrostatic model. Figure 4 shows the schematic of the SPICE equivalent
 161 circuit model of one cell in the panel. The physical development of the signal
 162 in the pixel was not modeled. It was introduced as an impulse at capacitor
 163 C_{pixel} .

164 The full SPICE model connected all the neighboring cells to form a 5×5
 165 array of pixels. Larger array sizes are computationally expensive and pro-
 166 duce the same results. Figure 5 shows the signal produced by the central
 167 pixel in the array and also a smaller transient pulse induced in an adjacent
 168 neighboring electrode. The important qualitative attributes of the SPICE
 169 modeling included the pulse shape and the transient pulses on other lines.
 170 The signal induced in neighboring pixels had greatly reduced amplitude and
 171 the opposite polarity of the discharging cell.

172 2.2. Pixel dead time

173 During the discharge, electric current starts to flow between the pixel
 174 electrodes. This current results in voltage dropping on the quench resistor,
 175 reducing the electric field between the pixel's electrodes. In these conditions
 176 the pixel discharge is not sustained; the discharge terminates and the gas
 177 neutralizes. The time required for the pixel electric field to regain a strength

Figure 4: SPICE model of one cell of a commercial PDP. The parameters C , L and R are capacitances, inductances and resistances of a single cell coupled to it's neighbors. Dashed lines represent the cell's connections to other pixels.

178 sufficient to enable a new discharge is determined by an RC time constant,
 179 where R is the quench resistance and C is the effective pixel capacitance. For
 180 a quench resistance of $100 \text{ M}\Omega$ and approximately 2 pF effective capacitance,
 181 the RC time is 2×10^{-4} seconds. The pixel dead time was experimentally
 182 determined to be about three times this RC time constant. For the modified
 183 commercial PDPs reported here, the quench resistance was applied to an
 184 entire chain of 24 pixels serviced by one HV line, rather than a single isolated
 185 pixel.

186 The RC time constants, and thus the pixel dead time, should be optimized
 187 according to the following considerations:

- 188 • If the dead time is not sufficiently long and the positive ion cloud and/or
 189 the gas metastable states are not neutralized then the discharge can
 190 restart without an external trigger, giving rise to more than one pulse
 191 per incident particle.
- 192 • For gas recovery dead time longer than necessary, the observed signal
 193 rate would saturate at an unnecessarily low rate and the panel will lose
 194 efficiency at high irradiation rates.

Figure 5: SPICE simulation results for the output pulse from a discharging cell (bottom) and the signal induced in an adjacent neighboring electrode (top). The scope picture of a recorded signal in the bottom insert shows the same amplitude and time characteristic of the simulated signal.

195 The optimal dead time changes with the gas content, with values in the range
 196 between 0.1 ms to a few milliseconds per pixel.

197 3. Data Acquisition

198 The characteristics of the pulses induced in the panel were measured with
 199 a 1 gigasamples/sec (GSPS) digital oscilloscope or an evaluation board of the
 200 DRS4 chip [17]. The evaluation board was equivalent to a four channel, 5
 201 GSPS digital oscilloscope with control, readout and data storage performed
 202 by an external computer.

203 Extraction of the signals from the prototype PPS panels was done with
 204 a custom designed PCB readout card connected to the panel electrode pads.
 205 The signal was picked off of a termination resistance (R_t in Figure 2). These
 206 readout cards included attenuators for each readout line since the observed
 207 several volt signal amplitudes were too large for the readout electronics.

208 In order to instrument more readout lines and thus have a larger active
 209 area in the panel, a more elaborate DAQ system was used. For this purpose
 210 a portable version of the readout system for the ATLAS precision muon

chambers called MiniDAQ [18] was adopted. This implementation of the MiniDAQ system was capable of recording integrated pulse height and time relative to the trigger for up to 432 channels with a sub-nanosecond (0.78125 ns) least significant bit.

For position measurement scans, where only basic hit information was needed, either a Wiener NIMbox [19] module, configured as a 20 channel scaler, or a CAEN V560 16 channel scaler [20] was employed to acquire data. In these measurements, signal processing was done in three stages. The panel signals were first discriminated. One set of discriminator output logic signals were injected into the scalers. A second set of discriminator signals were logically OR'ed, and used to generate a 1 μ s long veto which was returned to the discriminators with a measured delay of 60 ns. This veto blocked counts in the scaler from the occurrence of later pulses that might occur in a panel.

For each of the above dedicated data acquisition methods, analysis software was written using LabVIEW [21] and C++/ROOT [22].

3.1. Radioactive sources

Because of the low rate of cosmic ray muons through the instrumented area of the panels, a number of measurements reported here were made by using radioactive β emitters: ^{90}Sr and ^{106}Ru . These measurements probed the panel sensitivity to the applied voltage by measuring hit rates, and gauged the position resolution. The ^{90}Sr source (3.7 mCi), produces, at the end of its decay chain a β spectrum with a maximum energy of 2.28 MeV [23]. A ^{106}Ru source, about 3 μ Ci at the time of the experiments here reported, yields a β energy spectrum end point of 3.54 MeV [24]. The sources were separated from the active pixel volume by various air gaps and the 2.23 mm glass plate of the PPS, resulting in substantial beta energy loss. Measurements with radioisotopes were self-triggered by the logical OR of all the readout channels after discrimination.

4. Measurements

The measurement results reported here included evaluation of the response of type VPA and MP panels (see Table 1) filled with various gas mixtures using Ar, CO₂, CF₄ and, for thermal neutron detection, ^3He . The panel response to radiation, background hit rates and the occurrence of discharge spreading were investigated using low energy β particles, γ rays, thermalized neutrons from radioactive sources and cosmic ray muons. Efficiency

246 and time response for a few gas mixtures and pressures were probed using
 247 cosmic ray muons. Position reconstruction and spatial resolution were ex-
 248 plored using a slit-collimated radioactive source whose position was set with
 249 a computer-controlled servo-motor arm.

250 4.1. Response to β sources

251 All panel types responded to the radiation emitted from ^{90}Sr and ^{106}Ru
 252 sources, with all of the tested gases. Panels were tested at pressures rang-
 253 ing from as low as 200 Torr to slightly below atmospheric pressure, because
 254 the tested PDPs were not designed for positive pressure. This paper reports
 255 measurements made at pressures from 600-730 Torr. Figure 6 shows a rep-
 256 resentative signal induced by a ^{90}Sr source irradiating an MP type panel.
 257 Similar signals were observed using β sources in a panel filled with Xe at
 600 Torr [4], sealed seven years before the observation [1].

Figure 6: A representative signal induced in a type MP panel (in Table 1), filled with 90% Ar and 10% CF_4 at 600 Torr. The large trace shows the negative discharge pulse. Other traces show transient activity on the nearest neighbor readout electrodes (see Figure 5 for comparison). Rise time was about 2 ns.

258 The signals from all the tested gases were characterized by large ampli-
 259 tudes of 1-10 V volts that depended highly on the gas content and panel type,
 260 as well as fast rise times, around 1 to 3 ns. These general features were also
 261 evident in the SPICE signal simulation shown in Figure 5. The large signals
 262

263 did not require amplification and sometimes required attenuation. For each
 264 test configuration of panel type, gas mixture, pressure and high voltage, the
 265 induced signal amplitudes were uniform, with approximately 2% variation.
 266 This can be seen in one case in Figure 7 and is expected for a Geiger type
 discharge.

Figure 7: Distribution of the amplitudes, attenuated by 20dB, for a panel (type VPA in Table 1) filled with 99% Ar and 1% CO₂ at 600 Torr operated at 860 V. The Gaussian fit shows that the dispersion around the mean is 2%.

267
 268 Two experiments were conducted to validate the COMSOL and SPICE
 269 models. In the first, a type MP panel (see Table 1) filled with a gas mixture of
 270 10% CF₄ in Ar at 600 Torr was used. The dependence of the signal amplitude
 271 on the applied voltage was measured, the operating voltage range was chosen
 272 for maximum signal rate with minimum source-free (background) rate. This
 273 was expected to be linear, based on the idealized capacitive discharge model
 274 expressed by the circuit in Figure 2. The waveform of a single pixel pulse
 275 at increasing HV was recorded. The signal amplitude was then fitted with
 276 a Gaussian function. Figure 8 displays the dependence of the means on the
 277 applied HV, confirming the expected linear relationship.

278 In a second experiment, a type VPA panel (see Table 1) filled with a gas
 279 mixture of 10% CF₄ in Ar at 600 Torr was used at fixed operating voltage
 280 of 1100V. The signal amplitude dependence on the number of readout lines
 281 instrumented was measured. During these measurements, unconnected elec-

Figure 8: Gaussian mean of the signal amplitude, attenuated by 20 dB, vs HV for a panel (type MP in Table 1) filled with 10% CF_4 in Ar at 600 Torr.

trodes were left floating. The exponential behavior of the data in Figure 9 shows that with five or more lines the amplitude of the signal reached an asymptotic value, consistent with the use of a 5×5 matrix for the SPICE electrical simulations.

4.1.1. Voltage scan

The PPS response to radioactive sources and the associated background (i.e. no source) were measured over a range of applied HV. Figure 10 presents an example of a voltage scan taken with a gas content of 1% CF_4 in Ar at 600 Torr. In this measurement one HV line was quenched with a 44 M Ω resistor and four readout channels were instrumented. For every applied voltage two measurements were taken, one in which a ^{106}Ru source was positioned in a fixed location above the panel's active area, and one with the source removed.

These measurements provided a relative rate dependence on the HV. The net rate appeared to reach a plateau at about 1150 V, extending for about 60 volts. The dead time is around 350 μs , so in this region the maximum fraction of hits potentially lost because of the dead time is below 12%. Importantly, the source-free rate remained very low for a large range of HV before gradually increasing at higher values of the applied HV. The source-free hit

Figure 9: Gaussian mean of the signal amplitude vs. number of connected readout lines. VPA panel filled with 10% CF_4 in Ar at 600 Torr.

Figure 10: Response to ^{106}Ru source (circles), background rate (triangles) and signal with background subtracted (crosses) vs. the applied voltage. Shown is the combined rate of four pixels in a panel (type VPA in Table 1) filled with 1% CF_4 in Ar at 600 Torr.

301 rate was primarily attributed to discharges resulting from spontaneous forma-

tion of ion pairs in the gas, from electron surface emission due to stochastic collisions and from photoelectric processes. At higher applied HV the probability for spontaneous ionization and regeneration increased leading to a higher background hit rate.

4.1.2. Quench resistor dependence

For a given panel and gas mixture, a characteristic response curve was generated, giving the dependence of the source induced hit rate on the HV quench resistance. This is shown in Figure 11, plotted as a function of the reciprocal of the line quench resistor. For this measurement the panel was filled with 1% CO₂ in Ar at 600 Torr and was operated at 815V. The radioactive source was ¹⁰⁶Ru and the hits were collected from four readout electrodes crossing a single HV line. The quench resistors cover the range from 10-600 MΩ.

Figure 11: Signal induced by ¹⁰⁶Ru source (circles) and background rate (squares) dependence of the reciprocal of the line quenching resistor. Panel is type VPA filled with 1% CO₂ in Ar at 600 Torr, operated at 815 V.

314

315 This measurement showed that for resistance values below 20 MΩ the
 316 recovery time was insufficiently long to prevent the formation of afterpulses.
 317 These afterpulses increased the measured hit rate. Conversely, for resistance
 318 values above about 100 MΩ the pixel's RC constant was too high for the
 319 applied source intensity. This was because the time between successive hits

320 from the source was less than the pixel recovery time, so that the observed hit
 321 rate saturated, being limited by the RC constant. For this specific gas mix-
 322 ture, pressure and source intensity, the working range of quench resistances
 323 was obtained where the measured hit rate was flat.

Figure 12: Net hit rate of four instrumented pixels at very high R_{quench} .

324 These measurements were extended to very high quench resistor values,
 325 shown in Figure 12, using exactly the same setup parameters as in Figure 11.
 326 This measurement probed the recovery time constant $\tau = \alpha \cdot RCN_P$ where
 327 α is the number of RC time constants needed for a cell's recovery, R is the
 328 quench resistance, C is the pixel's effective capacitance (described earlier)
 329 and N_P is the number of instrumented pixels. The slope of the linear fit
 330 to the data was 47 ± 1 pF. Using the measured value for the capacitance,
 331 $C = 2.7 \pm 1$ pF and $N_P = 4$, then $\alpha = 4.3 \pm 1.6$. This result suggested that,
 332 for the cell to become fully active after a discharge, the electric field must
 333 have returned to within a few percent of its pre-discharge strength. For a
 334 44 MΩ external quench resistance, as used for the experiment in Figure 10,
 335 the recovery time for a single HV line is around 500 μ s.

336 4.2. Measurements with cosmic ray muons

337 Cosmic muons were used to explore the PPS response to minimum ioniz-
 338 ing particles (MIPs). The main features investigated were the efficiency and

339 timing response. Uniformity was also measured. For these measurements
 340 an external plastic scintillator trigger was used. This trigger provided the
 341 necessary coincidence and timing of signals induced in the panel to cosmic
 342 muons.

343 The trigger hardware was formed by two scintillator paddles ($7.5\text{ cm} \times$
 344 10 cm) placed above and below the instrumented areas of the panel (see
 Figure 13).

Figure 13: Trigger setup with the panel in a sandwich of scintillators.

345 The trigger signal was the time coincidence of the discriminated pulses (20
 346 ns wide, NIM logic signals) from the two scintillator photomultipliers. The
 347 coincidence window of the panel and trigger was $2\text{ }\mu\text{s}$. The uncorrelated single
 348 count hit rate in each scintillator was tens of Hz, so the rate of accidental
 349 coincidences was negligible.
 350

351 4.2.1. Uniformity of response

352 Commercial PDPs are fabricated with tolerances not necessarily as strin-
 353 gent as required for detectors. As more HV and readout lines were instru-
 354 mented, variations in the count rates were observed on different parts of the
 355 panels. A study was performed to obtain a baseline measurement of the
 356 uniformity of the panel as a function of position.

357 Figure 14 shows the distribution of cosmic ray muon PPS hits per read-
 358 out line summed over the 30 HV lines instrumented. For this panel, the
 359 RMS fluctuation around the mean of 95.4 is less than 12%. This variation,

Figure 14: Hit map of cosmic rays acquired with a panel (type VPA in Table 1) filled with 1% CF_4 in Ar at 730 Torr and operated at 1040V. This panel had 24 readout and 30 HV lines instrumented for this experiment.

360 however, reflects the convolution of the panel non-uniformity with the trig-
 361 ger spatial non-uniformity, evaluated to be no more than 10% across the
 362 instrumented area of the panel. These variations are expected based on the
 363 non-uniformities of the thick film electrode printing technique used in PDP
 364 construction.

365 4.2.2. Secondary pulses

366 Secondary pulses, referred to here as secondaries, are defined as those
 367 pulses occurring after the primary one either on the same pixel (afterpulses)
 368 or in a different location as the result of discharge spreading. Discharge
 369 spreading is primarily caused by both drifting metastable species and by
 370 VUV photons propagating to nearby pixels. The results of the position
 371 scans (see Section 4.3) suggested that detrimental effects of secondaries are
 372 limited.

373 The frequency of secondaries is dependent on the panel geometry, high
 374 voltage, fill gas and pressure. The frequency and position distribution of
 375 secondaries was investigated with a VPA panel filled with a gas mixture of
 376 1% CF_4 in Ar at 730 Torr using cosmic ray muon data. Figures 15 and 16
 377 show the position and time separation of secondaries measured using this

378 panel. The data contained about 5000 muon triggered events of which 64%
 379 have a single hit (no afterpulse) and the remainder contain two or more hits.
 380 A similar measurement was done on a type MP panel with 10% CF₄ in
 381 Ar at 730 Torr at 910 V. Here the number of events with secondaries on
 382 any pixel neighboring the triggered readout pixel in a 1 μ sec window was
 383 directly counted on a digital sampling oscilloscope. The fraction of events
 with secondaries was 3%.

Figure 15: Secondary pulse readout line separation between the first hit of the event and the n^{th} hit in time. The gas is 1% CF₄ in Ar at 730 Torr in VPA panel.

384
 385 The number of secondary (1st, 2nd, 3rd, etc.) hits in a line decreased with
 386 distance from the primary hit location as shown in Figure 15. This shows
 387 that afterpulses and the discharge spreading are decreasing rapidly after the
 388 third line 7.5 mm away from the primary pulse. Although the secondary hits
 389 appeared mostly on a time scale of 100 ns or less, as shown in Figure 16, this
 390 did not preclude longer time scale processes such as metastable states or ion
 391 drift from initiating discharges.

392 4.2.3. Arrival time

393 The arrival time of the signal relative to the trigger was measured. Ar-
 394 rival time=0 corresponds to the passage of the muon through the panel. The
 395 important parameters of the signal time distribution are the mean, i.e. the

Figure 16: Secondary pulse time separation between the n -th hit of the event and the trigger hit for 1% CF_4 in Ar at 730 Torr.

discharge formation time, and the width, i.e. the fluctuation in the discharge formation time, that limited the timing resolution of the detector.

Cosmic ray muon data were acquired with different gas mixtures and pressures, and over a range of applied HV. Figure 17 shows the mean and Gaussian width of the muon arrival time distribution for various operating conditions.

The arrival time resolution, represented by the Gaussian width decreased as the HV increased. In these measurements no trigger timing data were available, so the effective time resolution was widened by the 25 ns least count timing of the data acquisition. In any case the effect of voltage with various gas mixture and pressures is clearly visible in Figure 17: the gas mixture with higher concentration of CF_4 yields faster timing.

Additional measurements were performed in which trigger time information was available. They displayed a trigger timing jitter of 1.8 ± 0.1 ns measured as the sigma of a Gaussian fit of the time difference between the two trigger scintillators. Figure 18 shows a cosmic ray muon arrival time distribution made with this trigger time subtraction. This measurement used a gas mixture of 20% CF_4 in ^3He at 730 Torr operated at 1035 volts. An intrinsic time resolution of 2.9 ± 0.3 ns was determined by fitting the primary arrival time peak, and after accounting for the trigger timing jitter.

Figure 17: Compilation of cosmic muon mean (top) and Gaussian width (bottom) of the arrival time distribution in various gas conditions. No trigger time subtracted (see text).

Figure 18: Cosmic ray muons arrival time distribution. Gas content: 20% CF₄ in ³He at 730 Torr and 1035 V. Trigger cable and electronic delay times accounted for a total of 69 ns with an error estimated to be ± 10 ns.

4.2.4. Cosmic ray muon efficiency estimation

A panel's sensitivity to MIPs can be estimated from cosmic ray muon detection experiments. For this purpose three definitions of efficiency were

419 used:

- 420 • A *raw efficiency*, ε_{raw} , was the ratio of the number of detected cosmic
421 ray muons to the number of triggers:

$$\varepsilon_{raw} = \frac{N(\text{trigger} \bullet \text{PPS})}{N_{\text{triggers}}} \quad (1)$$

422 where $N(\text{trigger} \bullet \text{PPS})$ was the number of trigger and PPS coinci-
423 dences.

- 424 • A panel efficiency, ε_{panel} was defined by and estimated from:

$$\varepsilon_{panel} = \frac{\varepsilon_{raw}}{A} \quad (2)$$

425 where A was the fractional acceptance, taken as the ratio of the instru-
426 mented panel area relative to the total trigger area. ~ 0.55 .

- 427 • A pixel efficiency was defined and estimated by,

$$\varepsilon_{\text{pixel}} = \frac{\varepsilon_{\text{panel}}}{f_{\text{pack}}} \quad (3)$$

428 where f_{pack} was the pixel packing fraction given in Table 1.

429 The *panel efficiency* of these modified display panels was about 6% to
430 13%, depending upon the HV, limited by the very thin gas gap and the small
431 pixel packing fraction. Figure 19 shows an example of the panel efficiency
432 for a gas mixture of 1% CF_4 in Ar at 600 Torr. These data showed a stable
433 muon detection rate over a 28 hour run.

434 The *pixel efficiency* was the efficiency for a single pixel to discharge when
435 an ionizing particle traverses it. A few considerations affected the estimation
436 of the pixel efficiency:

- 437 1. The trigger rate was uniform across the entire triggering area.
- 438 2. Only the pixel area was active with no significant fringe or edge effects.
439 The effective pixel size did not increase with the applied voltage. The
440 active area of a panel was determined by the packing fraction, estimated
441 for a VPA panel to be 23.5% (Table 1).

Figure 19: Example of panel efficiency for a panel, type VPA in Table 1, filled with 1% CF_4 in Ar at 600 Torr at an applied voltage of 1000 V.

- 442 3. The average number of primary ion pairs, N_P , was Poisson distributed.
 443 Using Ar as the host gas with 10% CF_4 [25] and a gas gap of $385 \mu\text{m}$, a
 444 cosmic ray muon passing through the tested panel produced an average
 445 of 0.95 ion pairs. The Poisson probability for a MIP to produce at least
 446 one ion pair in the panel was:

$$P(N_P > 0) = 1 - e^{-0.95} \approx 0.61 \quad (4)$$

447 The maximum possible efficiency for detecting a MIP in a single cell of these
 448 panels was 0.61, limited by the probability to generate at least a single ion-
 449 pair in the thin gas gap.

450 The panel efficiency and the single pixel efficiency based on the above
 451 assumptions are shown in Figure 20 as a function of operating voltage.

452 For the VPA panel, filled with 10% CF_4 in Ar at 730 Torr and operating
 453 at 1360 volts, the pixel efficiency was 55%, which was nearly 90% of the
 454 maximum possible efficiency of 61%. The observed efficiency rise with voltage
 455 is expected. The drop off at 1380V is a consequence of dead time caused by
 456 numerous pixels firing spontaneously at very high rates.

Figure 20: Efficiencies for a type VPA panel, filled with 90% Ar and 10% CF₄ at 730 Torr. (Triangles) –panel efficiency ϵ_{panel} for the instrumented region; (Circles)– single pixel efficiency ϵ_{pixel} ; (Dashed line)– the maximum possible single pixel efficiency for this panel’s gas pressure and gap size. The statistical error bars are smaller than the data points.

4.3. Position measurements and spatial resolution

In order to investigate the panel’s position sensitivity and estimate position resolution, a series of position scan measurements were done. In these measurements the relative position of a collimated radioactive source with respect to the PPS readout electrodes was reconstructed. A large working area was instrumented consisting of 20 readout lines $\times$ 30 HV lines. The collimated radiation source produced hit distributions. Fits to these hit distributions yielded a measure of the source position.

A computer controlled robotic arm mounted on an X-Y translatable axis performed automated position scans. A collimated ¹⁰⁶Ru source was attached at one end of the arm and positioned over the panel. The collimator consisted of a 2 cm thick graphite block with a 1.25 mm slit aperture between the source and glass substrate. Control software translated the source in both X and Y directions with a precision of about 2 μ m. At each step of the position scan, data were acquired for equal time intervals and signals from each readout channel were counted with a 20 channel scaler.

473 4.3.1. *Simulation of the collimated β source*

474 The investigation of the spatial response of the panel was augmented by
 475 a Monte Carlo simulation of the β source collimation and PPS material scat-
 476 tering. GEANT4 [26] simulations were used to evaluate the contribution of
 477 the scattering of the source electrons to the measured distribution of betas
 478 in the detector. The full simulation started with the β energy spectrum of
 479 the bare isotope, included scattering in the ceramic matrix within which the
 480 isotope was deposited, the collimator material and aperture, and the glass
 481 substrates of the panel. The emission of β s was in all directions, sampled ap-
 482 propriately from the energy distribution. The limited sampling in Figure 21
 483 shows the effect of the air scattering, the effectiveness of the collimation and
 484 the glass energy loss and dispersion, using a pencil beam sampled from the
 485 energy distribution. β s entering the panel experienced significant scattering
 486 and absorption in the front glass substrate, so much so that few were able to
 487 exit the panel through the back glass substrate.

488 The initial 1.25 mm collimated beam of β particles had spread at the
 489 entrance of the discharge gas volume to a distribution with full width at half
 490 maximum (FWHM) of about 2.6 mm with long non-Gaussian tails, as shown
 491 in Figure 22. The resulting “collimated” β beam inside the PPS thus also
 492 illuminated adjacent sense electrodes on each side of the targeted electrode
 493 under the graphite slit.

494 4.3.2. *Spatial resolution determination from data*

495 The intrinsic resolution was estimated from the convolution fit of the
 496 panel hit distribution using a Gaussian to represent the intrinsic resolution
 497 and a Breit-Wigner function that well described the Monte Carlo distribution
 498 around the peak region. Figure 23 displays the result of a single position scan
 499 run, using the ^{106}Ru source and acquiring data for 20 minutes at each point.
 500 The intrinsic resolution obtained for the 1 mm pixel pitch panel in Figure 23
 501 was $\sigma_i = 0.73 \pm 0.12$ mm.

502 This approach yielded an upper limit to the resolution because it ignored
 503 three systematics.

504 One was the absence of secondary β s in the simulations. These second-
 505 aries originated from the conversion of γ s (e.g., X-rays shown in Figure 21).
 506 While expected only at the few percent level, these β s produced a very broad
 507 distribution and were superimposed on the distribution from primary β s.

508 A second systematic effect arose from the lack of timing information in
 509 the readout method employed for these tests. In this open architecture panel

Figure 21: GEANT4 β scattering simulation with ^{106}Ru source. For illustration purposes the source is shown as a point source aimed at the PPS. The beam expands to fill the slit because of air scattering, then further diverges in the glass, as well as losing intensity.

about 1/3 of the hits yielded an afterpulse within a few tens of μsec . These afterpulses were mostly vetoed and did not register as hits. Nevertheless, less than 5% of the afterpulses incremented a scaler channel before the veto was applied.

The third systematic omission was that the simulation generated the distribution of β s at the entrance to the gas volume. This fails to account for the large angular distribution of the particles introduced by multiple scattering in the air column and in the glass, which would cause the distribution to spread significantly as it propagates through the gas volume.

In general, for each complete scan, the hit map from each step was fitted with a Breit-Wigner plus linear function to model the peak and long tails of the distribution. The position of the source, as seen by the detector, was then taken to be the value of the mean of the fit function. Figure 24 shows

Figure 22: GEANT4 simulation showing the expected distribution of β s from the slit collimated ^{106}Ru source inside the PPS cell gas volume. The Breit-Wigner fit was limited to the peak region (i.e. the continuous line).

Figure 23: Representative hit distribution induced in a 1 mm pixel pitch panel (type MP in Table 1), filled with 10% CF_4 in Ar at 600 Torr by the collimated ^{106}Ru source. The line represents the convolution fit (see text). The Gaussian width is reported.

523 reconstructed source positions for a series of 100 μm steps from a single
 524 position scan.

Figure 24: Results of the position scan using a type MP panel (Table 1), filled with 10% CF_4 in Ar. Each data point is the Breit-Wigner fit mean corresponding to the reconstructed position of the source.

525 4.3.3. Medium energy protons

526 In addition to the described position resolution results from a β particle
 527 source, similar results were obtained using a proton beam. A type VPA
 528 panel was exposed to a collimated, 226 MeV proton beam from an IBA C-235
 529 proton beam therapy accelerator. An experiment using the 1 mm diameter
 530 beam, with an intensity of 2×10^6 particles/sec- mm^2 demonstrated the beam
 531 position measurement to be consistent with the 2.5 mm pixel pitch [27].

532 4.4. Neutron detection

533 In collaboration with Reuter-Stokes (General Electric Co.) in Twins-
 534 burg, OH, a prototype PPS was evaluated as a detector capable of neutron
 535 detection with a low gamma ray interaction rate. A 2.5 mm pitch panel
 536 was filled with a gas mixture of 80% ^3He and 20% CF_4 at 730 Torr. Some
 537 600 instrumented pixels, almost 39 cm^2 , were exposed to thermal neutrons
 538 produced by various neutron sources (i.e., ^{252}Cf , $^{241}\text{Am-Be}$ and $^{239}\text{Pu-Be}$).

Figure 25: Sketch of setup for neutron measurements. The ^{252}Cf source in a high density polyethylene moderator. A ^{10}B -Al plate is interposed between the source and the panel for some measurements, and removed for others (see text). The underlying wood table surface is also fully covered with borated-aluminum to reduce the probability of events generated by neutron scatters.

539 The sources were encapsulated and nested in the center of a cylinder of high
 540 density polyethylene.

541 Hit rate measurements were performed with and without a ^{10}B -Al neu-
 542 tron mask between the source and the panel. The borated aluminum mask
 543 was 7.75 mm thick, and had a ^{10}B areal density of 50 mg/cm^2 . ^{10}B has a cross
 544 section of 3835 Barns for thermal neutrons. A calculation of thermal neutron
 545 transmission based on the above values yields 0.001%. The transmission of
 546 gammas is calculated to be 70%-80%. A GE proprietary measurement deter-
 547 mined that at most 0.1% of the source generated neutrons were transmitted
 548 by the mask.

549 The thermal neutron capture on ^3He resulted in the emission of a low en-
 550 ergy proton and a triton, sharing a total kinetic energy of 764 KeV. Since the
 551 interaction occurred essentially at rest, these particles were emitted isotrop-
 552 ically, with a range of 1 to 2 cm in the gas mixture of the panel. They were
 553 very highly ionizing, producing many hundreds of ion-pairs in the panel gas
 554 gap.

Figure 26: Rates measured by the 20 readout x 30 HV instrumented lines of the 2.5 mm pitch PPS device (type VPA in table 1) filled with 80% ^3He and 20% CF_4 at 730 Torr when exposed to a calibrated ^{252}Cf source at different values of the applied HV. Triangles– the total rate; Inverted triangles– rate with a neutron mask between source and panel (γ -component); Diamonds– the net rate (i.e. neutrons only) after subtracting the γ -component.

Results of two sets of measurements with and without the neutron source at different HV values are shown in Figure 26. After subtracting the γ contribution to the total rate, a plateau was observed in the measured neutron rate above 1015 volts.

The expected thermal neutron hit rate R_n was calculated as:

$$R_n = \sigma(^3\text{He}, n) \cdot \varepsilon_{det} \cdot \frac{\rho_{\text{He}}}{M} \cdot \tau \cdot \Phi_n \cdot A \quad (5)$$

where $\sigma(^3\text{He}, n)$ is the ^3He thermal neutron absorption cross section at 0.025 eV = 5327 ± 10 barns [28]; A was the instrumented panel area (20×30 pixels $\sim 39 \text{ cm}^2$); $\rho_{\text{He}} = 1.11 \cdot 10^{-4} \text{ g/cm}^3$ and $M = 5.01 \cdot 10^{-24} \text{ g}$ based on the density of ^3He in the panel under lab conditions; and $\tau = 385 \mu\text{m}$ was the thickness of the panel gas gap. The thermal neutron flux incident on the instrumented region of panel, Φ_n , was determined by a detailed GEANT4 MC calculation, and also with a direct measurement. The former yielded a flux of 3.4 ± 0.01 (statistical) Hz cm^{-2} , and the latter $3.8 \pm 0.4 \text{ Hz cm}^{-2}$. The measurement error was dominated by an estimated 10% systematic uncertainty. The mea-

569 sured flux value was used. The factor ε_{det} represented the efficiency to detect
 570 the low energy breakup fragment passing through the instrumented area of
 571 the panel.

572 Using Eq. 5 with the above values for the tested configuration the calcu-
 573 lated rate was $0.7 \pm 0.1 \times \varepsilon_{det}$ Hz. The measured rate at the last point of
 574 Figure 26 was 0.67 ± 0.04 Hz. The comparison of the predicted and measured
 575 rates suggests that, within an error dominated by the measurement of the
 576 thermal neutron flux, the net efficiency, ε_{det} , to detect the captured neutron
 577 breakup fragments was consistent with unity. The absolute efficiency for
 578 thermal neutron detection was

$$\varepsilon_n = \frac{R_n}{\Phi_n \cdot A} = 0.005 \pm 0.001 \text{ (systematic)} \quad (6)$$

579 The error was dominated by systematic uncertainty of the thermal neutron
 580 flux at the panel. The low efficiency was due to the minute amount of ^3He at
 581 low pressure in the 0.38 mm gas gap. By comparison, a commercial neutron
 582 counter [29] with a 25 mm radius tube and pressurized with ^3He to 4 atm
 583 has an efficiency for thermal neutrons of 62%.

584 Low sensitivity for γ detection is a desirable attribute of neutron detec-
 585 tors. A measurement of the panel efficiency for γ particles was conducted by
 586 directly irradiating the panel with an intense γ source, ^{137}Cs with an activity
 587 of 8.5 mCi, set at a distance such that the panel received a rate of $\approx 3 \times 10^5$
 588 γ/sec ($\pm 10\%$) over the instrumented region. Table 2 reports the results for
 589 the γ -efficiency and corresponding neutron efficiency for a selection of HV
 590 settings. While this γ efficiency is not considered low [30], it can be further
 591 reduced principally by using thinner substrates, “thin-film” ($< 1 \mu\text{m}$) rather
 592 than thick-film ($\sim 25 \mu\text{m}$) electrodes and by reducing the thickness of the
 593 dielectric around each pixel.

Table 2: γ irradiation test results. The γ -efficiency is the ratio of hit rate from the ^{137}Cs source exposure and the measured γ dose rate over the panel area. The neutron efficiency is the ratio of the number of hits collected at the corresponding HV and the measured thermal neutron rate over the active area of the panel.

HV(V)	γ -efficiency	n-efficiency	ratio
970	$3.0 \pm 0.8 \cdot 10^{-7}$	$1.7 \pm 0.3 \cdot 10^{-3}$	$1.8 \pm 0.8 \cdot 10^{-4}$
1000	$3.8 \pm 0.6 \cdot 10^{-6}$	$3.2 \pm 0.5 \cdot 10^{-3}$	$1.2 \pm 0.4 \cdot 10^{-3}$
1030	$2.5 \pm 0.4 \cdot 10^{-5}$	$4.6 \pm 0.7 \cdot 10^{-3}$	$5.5 \pm 1.7 \cdot 10^{-3}$

594 In a final test intended to evaluate position sensitivity to thermal neu-
 595 trons, a ^{10}B -Al neutron mask with a 5 mm wide slit was interposed between
 596 the neutron source and the panel. The source was located far from the slit
 597 aperture, at a distance much larger than the slit width, to approximate a
 598 uniform flux of neutrons and γ s incident on the panel. The resulting dis-
 599 tribution in Figure 27 shows a peak over a much smaller background. The
 600 Gaussian plus linear fit gives a sigma of 1.11 readout lines, or 2.8 mm. The
 601 corresponding FWHM is 6.6 mm, in rough agreement with the 5 mm of the
 602 slit dimension.

Figure 27: Result of the illumination of a panel (type VPA in Table 1) filled with 80% ^3He and 20% CF_4 at 730 Torr at 980 V with an intense ^{241}Am -Be source with a 5 mm collimator.

603 5. Summary

604 This research was intended to demonstrate the potential of the plasma
 605 panel sensor as an inexpensive, hermetically sealed, scalable, high resolu-
 606 tion and granularity, fast timing, high performance detector for a variety
 607 of sources and applications, even in an intense radiation and magnetic field
 608 environment. Test results on prototypes, adapted directly from commercial
 609 monochromatic plasma display panels, are reported here. Pulses induced

in the panels were systematically characterized, expanding on previously reported laboratory results [27, 31–33]. The results showed that high gain, fast time response, high spatial resolution and high granularity are achievable. The first prototype detectors successfully measured minimum ionizing particles, betas, protons, gammas and thermal neutrons from radioactive sources. Spatial resolution comparable with the pitch of the device and a time resolution as fast as 2 to 3 ns was measured. We are now investigating devices using discharge cells with better cell physical and electrical isolation, a longer drift space and higher fill factors. This should lead to a reduced level of discharge spreading, lower capacitance and faster discharge times (nanoseconds or lower) and very high position resolution. Deeper cells with longer interaction paths will increase the detector efficiency. Finally, the transition to devices fabricated using much thinner substrates will enhance transmission of highly ionizing particles while reducing secondary particle and photon generation.

Acknowledgment

Development of the PPS project was funded by the U.S. Department of Energy (DOE) - Office of Nuclear Physics Small Business Innovation Research grant award numbers DE-SC0006204 and DE-FG02-07ER84749 to Integrated Sensors, U.S. DOE, Office of Nuclear Physics, Applications of Nuclear Science and Technology grant to Oak Ridge National Laboratory, operated by UT-Battelle, LLC for the U.S. DOE, and DOE - Office of High Energy Physics grant number DE-FG02-12ER41788 to the University of Michigan. The research at Tel Aviv University was supported by the I-CORE Program of the Planning and Budgeting Committee and the Israel Science Foundation (grant number 1937\12). Funding for scientific exchange and collaboration between Tel Aviv University and the University of Michigan was provided by the Israel-American Binational Science Foundation, grant number 1008123.

Disclaimer: This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise

646 does not necessarily constitute or imply its endorsement, recommendation,
 647 or favoring by the United States Government or any agency thereof. The
 648 views and opinions of authors expressed herein do not necessarily state or
 649 reflect those of the United States Government or any agency thereof.

650 References

- 651 [1] D.S. Levin *et al.*, “Development of a plasma panel muon de-
 652 tector” Nuclear Instruments and Methods in Physics Volume
 653 652, Issue 1, 1 October 2011, Pages 315-318, ISSN 0168-9002,
 654 <http://dx.doi.org/10.1016/j.nima.2010.07.076>
- 655 [2] P.S. Friedman *et al.*, “Large-Area Plasma-Panel Radiation Detectors for
 656 Nuclear Medicine Imaging to Homeland Security and the Super Large
 657 Hadron Collider”, International Display Symposium, Seattle, WA, May
 658 2010, arXiv:1007.0487v1 [physics.ins-det]
- 659 [3] R. Ball *et al.*, “Plasma Panel Detectors for MIP Detection for the SLHC
 660 and a Test Chamber Design”, IEEE Nuclear Science Symposium Confer-
 661 ence Record, Orlando, (2009) 1321-1327 arXiv:1007.0486 [physics.ins-det]
- 662 [4] P. S. Friedman, “A New Class of Low Cost, High Performance Radiation
 663 Detectors”, 2005 IEEE NSS-MIC Conference Record, pp. 2815-2822
- 664 [5] P. S. Friedman and R.A. Stoller, US Patents 7,332,726 (2008), 7,518,119
 665 (2009), 7,564,039 (2009), 7,683,340 (2010), 7,696,485 (2010), 7,902,516
 666 (2011), 7,982,191 (2011), 8,158,953 (2012), 8,389,946 (2013) and 8,710,449
 667 (2014)
- 668 [6] R. Ball *et al.*, “Progress in the Development of Plasma Panel Radiation
 669 Detectors”, IEEE Nuclear Science Symposium Conference, (Knoxville,
 670 TN), Paper N50-7 (November 3, 2010) arXiv:1101.0045 [physics.ins-det]
- 671 [7] J. P. Boeuf “Plasma display panels: physics, recent developments and
 672 key issues”, J. Phys. D: Appl. Phys. 36 (2003) R53R79 (February 2003)
- 673 [8] Glenn F. Knoll “Radiation detection and measuremen”, fourth edition,
 674 ISBN: 978-0-470-13148-0

- 675 [9] M.J. Druyvesteyn and F.M. Penning “The Mechanism of Electrical Dis-
676 charges in Gases of Low Pressure” Rev. Mod. Phys. 12 (1940) 87 [Erratum
677 ibid. 13 (1941) 72]
- 678 [10] A. V. Phelps and J. P. Molnar “Lifetimes of Metastable States of Noble
679 Gases” Phys. Rev. 89, 12021208 (1953)
- 680 [11] H. Raether, Zeits. f. Physik 112, 464 (1939)
- 681 [12] J. M. Meek, “A Theory of Spark Discharge”, Physical Review V.57
682 (1940)
- 683 [13] M. Atac, A.V. Tollestrup, D. Potter, “Self-quenching Streamers” Nu-
684 clear Instruments and Methods 200 345 (1982)
- 685 [14] COMSOL Multiphysics. [Online] COMSOL Inc.
686 <http://www.comsol.com/products/multiphysics>
- 687 [15] <http://www.home.agilent.com/>
- 688 [16] L. W. Nagel and D. O. Pederson, “SPICE (Simulation Program with
689 Integrated Circuit Emphasis)”, Memorandum No. ERL-M382, University
690 of California, Berkeley, Apr. 1973
- 691 [17] PSI DRS Chip Home Page: <http://drs.web.psi.ch>
- 692 [18] Y.Arai *et al.*, “ATLAS Muon Drift Tube Electronics” 2008 JINST 3
693 P09001, <http://iopscience.iop.org/1748-0221/3/09/P09001>
- 694 [19] [http://www.wiener-d.com/sc/modules/nim-modules/nimbox-](http://www.wiener-d.com/sc/modules/nim-modules/nimbox-npl20.html)
695 [npl20.html](http://www.wiener-d.com/sc/modules/nim-modules/nimbox-npl20.html). A custom firmware for the 4 units allowed the use of
696 all 20 NIM inputs as scalers.
- 697 [20] <http://www.caen.it/csite/CaenProd.jsp?parent=11&idmod=62>
- 698 [21] <http://www.ni.com/labview/>
- 699 [22] Rene Brun and Fons Rademakers, “ROOT - An Object Oriented Data
700 Analysis Framework”, Proceedings AIHENP’96 Workshop, Lausanne,
701 Sep. 1996, Nucl. Inst. & Meth. in Phys. Res. A 389 (1997) 81-86. See
702 also <http://root.cern.ch/>

- 703 [23] www.nucleide.org/DDEP_WG/Nuclides/Sr-90_tables.pdf
- 704 [24] A. Munoz *et al.*, “Energy deposition model based on electron scattering
705 cross section data from water molecules”, Journal of physics: Conference
706 Series 133 (2008) 012002, doi:10.1088/1742-6596/1331/1/012002
- 707 [25] A.Sharma “Transport Properties of operational gas mixtures used at
708 LHC” SLAC-JOURNAL-ICFA-16 (1998)
- 709 [26] S. Agostinelliae *et al.*, “Geant4a simulation toolkit”, Nuclear Instruments
710 and Methods in Physics Research Section A: Accelerators, Spectrometers,
711 Detectors and Associated Equipment Volume 506, Issue 3, 1 July 2003,
712 Pages 250-303
- 713 [27] P. S. Friedman *et al.*, “Plasma Panel Sensors for Particle and Beam
714 Detection”, 2012 IEEE NSS-MIC Conference Record, pp. 1775-1780
- 715 [28] J. Als-Nielsen and O. Dietrich “Slow Neutron Cross Sections for ^3He , B
716 and Au” Physical Review, vol. 133, Issue 4B, pp. 925-929
- 717 [29] http://www.ge-mcs.com/download/reuter-stokes/GE_14158-L.pdf
- 718 [30] United States Government Accounting Office, “ Neutron Detectors”,
719 report GAO-11-753 Sept. 2011
- 720 [31] Peter Friedman *et al.*, “Plasma Panel-Based Radiation De-
721 tectors”, J. Soc. Info. Display, 21/1 (2013), pp. 46-54 (doi:
722 10.1002/jsid.151),<http://arxiv.org/abs/1305.2277>.
- 723 [32] Silver, Y. *et al.* “Development of a Plasma Panel Radiation Detector:
724 Recent Progress and Key Issues” 2011 IEEE NSS-MIC Conference Record
725 pp. 1881-1885, (doi: 10.1109/NSSMIC.2011.6154379)
- 726 [33] R. Ball *et al.*, “Plasma Panel Detectors for Ionizing Parti-
727 cles”, Snowmass 2013 Instrumentation Frontier Whitepapers,
728 http://www.snowmass2013.org/tiki-download_file.php?fileId=67.