Optimization of high count rate event counting detector with Microchannel Plates and quad Timepix readout

A. S. Tremsin^{1,*}, J.V. Vallerga¹, J.B. McPhate¹, O. H. W. Siegmund¹

¹*Space Sciences Laboratory, University of California at Berkeley,*

Berkeley, CA 94720, USA

**Corresponding author: Tel: +1 (510) 642 4554 Email: ast@ssl.berkeley.edu*

Abstract

Many high resolution event counting devices process one event at a time and cannot register simultaneous events. In this paper a frame-based readout event counting detector consisting of a pair of Microchannel Plates and a quad Timepix readout is described. More than 10^4 simultaneous events can be detected with a spatial resolution of $\sim 55 \mu\text{m}$, while $>10^3$ simultaneous events can be detected with $<10 \mu\text{m}$ spatial resolution when event centroiding is implemented. The fast readout electronics is capable of processing >1200 frames/sec, while the global count rate of the detector can exceed 5×10^8 particles/s when no timing information on every particle is required. For the first generation Timepix readout, the timing resolution is limited by the Timepix clock to 10-20 ns. Optimization of the MCP gain, rear field voltage and Timepix threshold levels is crucial for the device performance and that is the main subject of this paper. These devices can be very attractive for applications where the

photon/electron/ion/neutron counting with high spatial and temporal resolution is required, such as energy resolved neutron imaging, Time of Flight experiments in lidar applications, experiments on photoelectron spectroscopy and many others

1. Introduction

Event counting detectors, consisting of multiple independently operating readout channels, allow detection of multiple simultaneous events or detection of particles at high counting rates, which is important for many applications. The spatial resolution and image formats in such detectors are in many cases limited by the number of readout channels, as in case of multianode photomultiplier tubes. At the same time many high resolution event counting devices process one event at a time and cannot register simultaneous events. In this paper we describe an event counting detector with a Timepix [1] frame-based readout chips coupled to a stack of Microchannel Plates (MCPs). The low noise of the Timepix readout allows operation at MCP gains as low as 10^4 - 10^5 , substantially improving its counting rate capabilities and extending the lifetime of the detector.

The high resolution photon/ion/electron/neutron counting capabilities of Microchannel Plate (MCP) detectors have been demonstrated previously with several readout technologies to timing resolution of ~ 10 ps and spatial resolution limited by the present commercial MCP pore geometry (~ 5 - 10 μm) [2]-[5]. The unique feature of an MCP electron amplifier is to provide gains in excess of 10^7 per event while preserving the location within a single pore. It is the resolution of the readout of a particular detector which determines the spatial resolution of the device. The accurate event location can be achieved with either fine pitch readouts or alternatively with relatively course readouts through event centroiding. A fine pitch readout

43 matching the MCP pore sizes has to be utilized in the direct event encoding, e.g. in image
44 intensifiers producing a high resolution image at the phosphor screen. An optical magnification
45 can be implemented to match the pitch of CCD or CMOS readouts to the fine resolution of the
46 image intensifier. However, detectors requiring single event counting capabilities utilize position
47 schemes where the electron cloud from the MCP is used to determine the event position and
48 time. It was shown with Cross Strip (XS) anodes [5] and CMOS readouts [6] that 5-10 μm
49 resolution can be achieved with relatively coarse readouts (50-600 μm) through event
50 centroiding.

51 One of the crucial characteristics of event centroiding detectors is the time required to process an
52 event. That time defines the counting rate capabilities of the detector. In devices with a low
53 number of electronics channels (e.g. XS or cross delay line anodes) the events overlapping
54 within the processing time cannot be disentangled and are misplaced by the centroiding
55 algorithms and thus need to be recognized and rejected. Another challenge of event centroiding
56 readouts is simultaneous detection of multiple events, required for some applications where
57 signals arrive in bursts, e.g. in Time of Flight (TOF) applications with pulsed sources. Frame
58 based readouts, allowing simultaneous detection of multiple events per single frame, are very
59 attractive for such applications. The high spatial resolution of an MCP detector with Timepix
60 readout has already been demonstrated [7], but only at a limited counting rate of few KHz per
61 cm^2 . The limiting factor on the counting rate was the relatively slow frame rate of the serial
62 Timepix readout electronics [8]. A high counting rate exceeding 200 MHz per cm^2 area was also
63 demonstrated with spatial resolution of $\sim 55 \mu\text{m}$. Recent development of fast parallel readout
64 electronics for a quad Timepix (28x28 mm^2 area) [6],[9] capable of readout speeds of ~ 1200
65 frames/sec allows high resolution event counting with relatively high rates without degradation

of spatial resolution due to event overlaps. It also enables simultaneous detection of multiple events within a single frame. One of the main limitations of such a detector is its relatively small area ($28 \times 28 \text{ mm}^2$) limited by the size of the Timepix quad (2x2 chips) readout, although a 2xN chip detector configuration is possible in the future as only one side is required for the Timepix wirebonding.

2. Detector configuration and modes of operation

The detector configuration is shown in Fig. 1. A chevron stack of MCPs ($\sim 10 \text{ }\mu\text{m}$ pores on $12 \text{ }\mu\text{m}$ centers, 5 cm diameter) is placed above a quad Timepix readout in a vacuum enclosure operating at $\sim 10^{-6}$ Torr pressures. The signal from the Timepix chips are transferred at 100 MHz to a pair of Spartan 3 FPGA in parallel mode simultaneously from all 4 chips over 128 lines. A readout time of $\sim 300 \text{ }\mu\text{s}$ is required to read the entire quad assembly, during which no events can be detected. After that the shutter of Timepix readout can be open again. The data is subsequently transferred to a data acquisition computer over a 10 Gb s^{-1} interface. There are three possible modes of detector operation for the present generation of the Timepix ASIC:

➤ Mode 1: Event counting

- Up to 11000 counts/pix/frame
- Global event rate $> \text{GHz}$
- Spatial resolution $55 \text{ }\mu\text{m}$
- Timing resolution - frame length

➤ Mode 2: Event Timing

- 1 event/pix/frame
- Global event rate $\sim 25 \text{ MHz}$

- 88 ○ Spatial resolution 55 μm
- 89 ○ Timing resolution – tunable, minimum 10 ns
- 90 ○ Timing range - 11000 time bins

91 ➤ **Mode 3: Event centroiding**

- 92 ○ Charge is measured in each pixel
- 93 ○ Global event rate ~3 MHz
- 94 ○ Spatial resolution ~10 μm
- 95 ○ Timing resolution - frame length

96 **3. Optimization of detector parameters**

97 The performance of MCP/Timepix detector can be optimized for a particular mode of operation
98 and a certain set of parameters needs to be established for a particular type of experiment. The
99 flexibility of this detector allows its tuning to meet various, sometimes conflicting, requirements
100 without change in the hardware. For example, for applications where the event counting has to
101 be performed at very high counting rates, the gain of MCP stack has to be as low as possible to
102 prevent count rate saturation due to pore charging and to extend the lifetime of the detector. The
103 charge footprint has to be as small as possible to occupy only one Timepix pixel for most events.
104 The imaging with the highest spatial resolution, on the other hand, requires implementation of
105 event centroiding and thus spreading the charge over several pixels, leading to operation at a
106 higher detector gain and lower count rates mainly due to the limitation of the readout electronics.
107 Operation of the detector at the highest detection efficiency can be achieved by optimization of
108 the MCP biases for the detection of a particular particle. In this section the detector
109 characteristics are measured as a function of MCP gain, Timepix threshold and rear field voltage.

110 In the results presented below the top MCP was biased at 1100V and bottom MCP was biased at
111 900V unless noted otherwise.

112 **3.1. *High resolution imaging with event centroiding***

113 The spatial resolution of MCP/Timepix detector can be improved beyond the 55 μm pixel size by
114 the implementation of event centroiding [6],[7],[10]. In this mode the charge value in a pixel
115 needs to be measured and each event shall excite at least 3x3 pixels for the accurate event
116 localization down to a single pore resolution. A higher MCP gain, lower rear field and lower
117 Timepix threshold all lead to a larger event footprint. However, when the footprint is too large
118 the signal to noise ratio in each pixel becomes smaller and the detected count rate is reduced as
119 events start overlapping in a single frame. Therefore an optimal set of parameters can be
120 determined for the high spatial resolution imaging.

121 Fig. 2 shows images obtained with our detector in a high counting mode (Fig. 1.a) and a high
122 spatial resolution mode (Fig. 1.b, 1.c). The size of the footprints on the anode shown in Fig. 3
123 can be optimized by the variation of MCP voltage bias, and the acquisition shutter length should
124 also be tuned for a particular incoming flux in order to avoid event overlaps as shown in Fig. 3.c.
125 The raw integrated images (no centroiding) in that case suffer from the blurring by the wide
126 charge footprint, as shown in Fig. 3.d-f. The optimum charge width for our particular detector
127 configuration was found to be at 1100V bias on the front MCP, as shown in Fig. 4.
128 Simultaneously with the increased number of pixels affected by the detected particle, the number
129 of particles detected can also increase as more events appear above the Timepix threshold when
130 the charge is divided between many pixels, as demonstrated in Fig. 5. (Although some of them
131 cannot be used for the accurate centroiding if they are narrower than 3 pixels in diameter.) If
132 same detector settings are used in a high counting mode (Mode 1) the spatial resolution will be

substantially degraded as shown by the cross sections (Figs. 6 and 7) through the image of Fig. 2. Therefore a different set of parameters (Timepix threshold, MCP gain, rear field) has to be set for various modes of operation.

3.2. *Spatial resolution versus Timepix threshold*

One of the obvious ways to improve the spatial resolution of Mode 1 is to increase the threshold value of Timepix readout and discriminate those “wing” pixels for wide charge footprints, as shown in Figs. 8 and 9. However, better spatial resolution is achieved at the expense of detection efficiency, as some low gain events are then not detected. A new generation of Timepix with 40 Mevents/chip sparsified readout [11] will enable acquisition with higher detection efficiency as low threshold levels can still be used and cluster analysis can be implemented to bring all events into one 55 μm pixel of the readout.

3.3. *Event footprint versus rear field*

Another parameter which may affect the charge footprint in our detector is the strength of the electric field in the gap between the MCP stack and Timepix readout. It was observed that for the sub-1 mm gap in our current device there was no substantial variation of event footprints for the biases varied between 300 and 600 V, Fig. 11. It is the reduction of the distance which should be implemented for the minimization of the charge footprint, if needed.

3.4. *Timing of multiple simultaneous events*

One of the attractive features of the MCP/Timepix detectors is their ability to detect multiple (up to tens of thousands) simultaneous events, with both event position and timing resolved for each particle. That is important for some experiments such as energy resolved neutron imaging at resonance and Bragg edge energies, where many particles are to be detected within a short period

155 of time. However, the timing of events is limited to only one particle/pix/frame for the first
156 generation of Timepix readouts, thus requiring optimization of the length of the acquisition
157 shutter. In our experiments we demonstrate that even for the high fluxes, when multiple events
158 hit one pixel in a single shutter, we can still accurately recover the timing profile of the incoming
159 flux, Fig. 12. The timing resolution of our device is determined by the 14 bit depth of the pixel
160 counter and thus only 11800 time bins can be recorded in one shutter, although separate shutters
161 in our system can have various lengths and timing resolution.

162 **4. Conclusions**

163 The MCP/Timepix detectors with fast parallel readout capable of different modes of operation
164 (high spatial resolution, high counting rate or event timing) require optimization of detector
165 parameters (MCP gain, bias voltages and threshold values). Higher MCP gain leads to charge
166 spread over several pixels and that decreases the spatial resolution of high rate or timing mode,
167 but at the same time it improves the detection efficiency as more low-gain events appear above
168 the readout threshold. Therefore MCP gain and the Timepix threshold level should be adjusted
169 between high count rate and high spatial resolution modes of operation. It was also determined
170 that the rear field value has very little effect on the charge footprint (within 300-600 V range).
171 The ability to operate with multiple shutters per single trigger allows the measurement of the
172 time dependence of the input radiation even at very high count rates (> 100 MHz) if the input
173 flux is periodic. However, the duration of the acquisition frame needs to be adjusted for a given
174 input event rate to prevent event overlaps within a single frame, although post-experiment
175 overlap correction can be also implemented for the periodic input fluxes [12].

Acknowledgements

We would like to acknowledge the generous donation of Vertex 5 FPGAs, Vivado design suite and DK-K7-CONN-G connectivity kit by Xilinx Inc. of San Jose, California through their Xilinx University Program. The detector used in these experiments was developed within the Medipix collaboration. This work was supported in part by the U.S. Department of Energy under STTR Grants No. DE-FG02-07ER86322, DE-FG02-08ER86353 and DE-SC0009657.

References

- [1] X. Llopart, R. Ballabriga, M. Campbell, L. Tlustos, W. Wong, "Timepix, a 65 k programmable pixel readout chip for arrival time, energy and/or photon counting measurements", Nucl. Instr. and Meth. A 581 (2007) 485.
- [2] A. Vredenburg, W.G. Roeterdink, M.H.M. Janssen, "A photoelectron-photoion coincidence imaging apparatus for femtosecond time-resolved molecular dynamics with electron time-of-flight resolution of $\sigma = 18$ ps and energy resolution $\Delta E/E = 3.5\%$ ", Rev. Sci. Instr. 79 (2008) 063108.
- [3] A. S. Tremsin, G. V. Lebedev, O. H. W. Siegmund, J. V. Vallerga, J. S. Hull, J. B. McPhate, C. Jozwiak, Y. Chen, J. H. Guo, Z. X. Shen, Z. Hussain, "High spatial and temporal resolution photon/electron counting detector for synchrotron radiation research", Nucl. Instr. Meth. A 580 (2007) 853.
- [4] R. Bellazzini, G. Spandre, M. Minuti, A. Brez, L. Baldini, L. Latronico, N. Omodei, C. Sgro', J. Bregeon, M. Razzano, M. Pinchera, A.S. Tremsin, J.B. McPhate, J.V. Vallerga, and O.H.W. Siegmund, "Single Photon Imaging at ultra-high resolution", Nucl. Instr. Meth. A. 591 (2008) 125.

- [5] O. H. W. Siegmund, A. S. Tremsin, J. V. Vallerger, J. S. Hull, R. Raffanti, "Development of cross strip MCP detectors for UV and optical instruments", Proc. SPIE 74350L (2009).
- [6] A. S. Tremsin, J. V. Vallerger, J. B. McPhate, O. H. W. Siegmund, R. Raffanti, "High Resolution Photon Counting With MCP-Timepix Quad Parallel Readout Operating at > 1KHz Frame Rates", IEEE Trans. Nucl. Sci. 60 (2013) 578.
- [7] A. S. Tremsin, J. V. Vallerger, J. B. McPhate, O. H. W. Siegmund, W. B. Feller, L. Crow, R. G. Cooper, "On the possibility to image thermal and cold neutron with sub-15 μm spatial resolution", Nucl. Instr. Meth. A592 (2008) 374.
- [8] Z. Vykydal, J. Jakubek, S. Pospisil, "USB interface for Medipix2 pixel device enabling energy and position-sensitive detection of heavy charged particles", Nucl. Instr. Meth. A 563 (2006) 112.
- [9] J.V. Vallerger , Rick Raffanti, A.S. Tremsin, J.B. McPhate, and O.H.W. Siegmund, "MCP detector read out with a quad Timepix at kilohertz frame rates", J. Instrum. JINST 6 (2011) C01049.
- [10] A. S. Tremsin, J. B. McPhate, J. V. Vallerger, O. H.W. Siegmund, W. B. Feller, E. Lehmann, A. Kaestner, P. Boillat, T. Panzner, U. Filges, "Neutron radiography with sub-15 μm resolution through event centroiding", Nucl. Instr. Meth. A 688 (2012) 32.
- [11] T. Poikela, J. Plosila, T. Westerlund, M. Campbell, M. De Gaspari, X. Llopart, V. Gromov, R. Kluit, M. van Beuzekom, F. Zappon, V. Zivkovic, C. Brezina, K. Desch, Y. Fue, A. Kruthe, "Timepix3: a 65K channel hybrid pixel readout chip with simultaneous ToA/ToT and sparse readout", Journal of instrumentation 9 (2014) C05013.
- [12] A.S. Tremsin, J.V. Vallerger, J.B. McPhate, O.H.W. Siegmund, "Optimization of Timepix count rate capabilities for the applications with a repetitive input signal", J. Instrum. JINST 9 (2014) C05026.

5. Figure captions

Fig. 1. Schematic diagram of an MCP/Timepix event counting detector. The active area of detector is limited by the quad array of Timepix chips to $28 \times 28 \text{ mm}^2$. Fast parallel readout (x32 per chip) allows ~ 1200 frames/sec with $\sim 300 \text{ }\mu\text{s}$ readout time. Multiple simultaneous events can be detected. Detector contains nearly independently operating 262144 pixels, each $55 \times 55 \text{ }\mu\text{m}^2$ in area. Timing of event can be measured relative to external trigger.

Fig. 2. UV photon images of shadow masks obtained with MCP/Timepix detector. (a) Mode 1: photon counting mode with $55 \text{ }\mu\text{m}$ resolution, high count rate. The white line indicates the area of cross section shown in Figs. 6-8. (b),(c) – Mode 3: high resolution with event centroiding. Single pores are visible in (c) demonstrating the limit due to the MCP pore size of $\sim 10 \text{ }\mu\text{m}$.

Fig. 3. (a)-(c) The footprint of individual photons on the Timepix readout obtained at , 1.1 and 1.2 kV front MCP biases. The higher gain leads to wider charge spread. (d)-(f) – the raw UV photon images integrated at the same biases with no event centroiding. The loss of spatial resolution is obvious due to a wide charge spread at high MCP gains. The Timepix threshold was set at 1.88 kelectrons.

Fig. 4. The projection of charge footprint on one axis measured at various MCP biases/gains. The optimal charge footprint (~ 5 fingers full width) is at 1100V front MCP bias.

Fig. 5. Measured average charge footprint area and the number of detected events as a function of front MCP bias. More events are detected at higher gains and the average footprint area also increases.

237 **Fig. 6.** Cross section through the image area shown in Fig. 2.a measured at various front MCP
238 biases.

239 **Fig. 7.** Zoomed area (one peak) of Fig. 6 demonstrating the decrease of the spatial resolution in
240 raw images at high MCP gains and low Timepix threshold value.

241 **Fig. 8.** Same as Fig. 7, except measured at various Timepix threshold values. Higher Timepix
242 threshold values improve spatial resolution.

243 **Fig. 9.** The average event footprint area and number of detected events measured as a function of
244 Timepix threshold value. The highest spatial resolution is achieved at the expense of detection
245 efficiency.

246 **Fig. 10.** Same as Fig. 5, except measured at higher Timepix threshold.

247 **Fig. 11.** Measured average charge footprint area and the number of detected events as a function
248 of rear field voltage.

249 **Fig. 12.** Time distribution of UV flux intensity from a mercury vapor penray lamp (periodic with
250 120 Hz frequency) is measured by the detector. The sharp peak from the switching power supply
251 at ~8.4 ms is measured in detail in (b) and (c). Various time ranges can be selected with the
252 timing resolution determined by the Timepix clock frequency and 14 bits depth of pixel counter.
253 The shortest shutter of 0.2 ms allows ~20 ns timing resolution. Only one event/pix/frame is
254 allowed by current generation of Timepix readout. Multiple shutters per external trigger can be
255 measured with ~300 μ s readout time between them.

256

257

258

259 **Fig. 1.** Schematic diagram of an MCP/Timepix event counting detector. The active area of
 260 detector is limited by the quad array of Timepix chips to $28 \times 28 \text{ mm}^2$. Fast parallel readout (x32
 261 per chip) allows ~1200 frames/sec with ~300 μs readout time. Multiple simultaneous events can
 262 be detected. Detector contains nearly independently operating 262144 pixels, each $55 \times 55 \text{ }\mu\text{m}^2$ in
 263 area. Timing of event can be measured relative to external trigger.

264

Fig. 2. UV photon images of shadow masks obtained with MCP/Timepix detector. (a) Mode 1: photon counting mode with 55 μm resolution, high count rate. The white line indicates the area of cross section shown in Figs. 6-8. (b),(c) – Mode 3: high resolution with event centroiding. Single pores are visible in (c) demonstrating the limit due to the MCP pore size of $\sim 10 \mu\text{m}$.

Fig. 3. (a)-(c) The footprint of individual photons on the Timepix readout obtained at , 1.1 and 1.2 kV front MCP biases. The higher gain leads to wider charge spread. (d)-(f) – the raw UV photon images integrated at the same biases with no event centroiding. The loss of spatial resolution is obvious due to a wide charge spread at high MCP gains. The Timepix threshold was set at 1.88 keelectrons.

282

283 **Fig. 4.** The projection of charge footprint on one axis measured at various MCP biases/gains. The
 284 optimal charge footprint (~5 fingers full width) is at 1100 front MCP bias.

285

286

287 **Fig. 5.** Measured average charge footprint area and the number of detected events as a function
 288 of front MCP bias. More events are detected at higher gains and the average footprint area also
 289 increases.

290

291

292

293 **Fig. 6.** Cross section through the image area shown in Fig. 2.a measured at various front MCP
294 biases.

295

296

297 **Fig. 7.** Zoomed area (one peak) of Fig. 6 demonstrating the decrease of the spatial resolution in
 298 raw images at high MCP gains and low Timepix threshold value.

299

300

301 **Fig. 8.** Same as Fig. 7, except measured at various Timepix threshold values. Higher Timepix
 302 threshold values improve spatial resolution.

303

304

305 **Fig. 9.** The average event footprint area and number of detected events measured as a function of
 306 Timepix threshold value. The highest spatial resolution is achieved at the expense of the
 307 detection efficiency.

308

309

310 **Fig. 10.** Same as Fig. 5, except measured at higher Timepix threshold.

311

312

313 **Fig. 11.** Measured average charge footprint area and the number of detected events as a function
 314 of rear field voltage.

315

316

317

318

319

320 **Fig. 12.** Time distribution of UV flux intensity from a mercury vapor penray lamp (periodic with
 321 120 Hz frequency) is measured by the detector. The sharp peak from the switching power supply
 322 at ~8.4 ms is measured in detail in (b) and (c). Various time ranges can be selected with the
 323 timing resolution determined by the Timepix clock frequency and 14 bits depth of pixel counter.
 324 The shortest shutter of 0.2 ms allows ~20 ns timing resolution. Only one event/pix/frame is
 325 allowed by current generation of Timepix readout. Multiple shutters per external trigger can be
 326 measured with ~300 μ s readout time between them.