Chemical characterization of surface precipitates in $\text{La}_{0.7}\text{Sr}_{0.3}\text{Co}_{0.2}\text{Fe}_{0.8}\text{O}_{3-\delta}$ as cathode material for solid oxide fuel cells

Yang Yu¹, Alexey Y. Nikiforov², Tiffany C. Kaspar³, Joseph C. Woicik⁴, Karl F. Ludwig^{1, 5}, Srikanth Gopalan^{1, 6}, Uday B. Pal^{1, 6} and Soumendra N. Basu^{1, 6, #}

¹ Division of Materials Science and Engineering, Boston University, Brookline, MA 02446, USA

² Photonics Center, Boston University, Boston, MA 02215, USA

³ Physical Sciences Division, Pacific Northwest National Laboratory, Richland, WA 99354, USA

⁴ Material Measurement Laboratory, National Institute of Standards and Technology, Gaithersburg, Maryland 20899, USA

⁵ Department of Physics, Boston University, Boston, MA 02215, USA

⁶ Department of Mechanical Engineering, Boston University, Boston, MA 02215, USA

Abstract

In this study, a strontium doped lanthanum cobalt ferrite thin film with 30% Sr on A-site, denoted as $\text{La}_{0.7}\text{Sr}_{0.3}\text{Co}_{0.2}\text{Fe}_{0.8}\text{O}_{3-\delta}$ or LSCF-7328, is investigated before and after annealing at 800 °C under CO_2 containing atmosphere for 9 hours. The formation of secondary phases on surface of post-annealed LSCF-7328 is observed using atomic force microscope (AFM) and scanning electron microscope (SEM). The extent of Sr segregation at the film surface is monitored using the synchrotron-based total reflection X-ray fluorescence (TXRF) technique. The bonding environment of the secondary phases formed on the surface is investigated by synchrotron-based hard X-ray photoelectron spectroscopy (HAXPES). Scanning transmission electron microscopy (STEM) and related spectroscopy techniques are used for microstructural and quantitative elemental analyses of the secondary phases on surface. These studies reveal that the secondary phases on surface consist of SrO covered with a capping layer of SrCO_3 . The formation of Co-rich phases is observed on the surface of post-annealed LSCF-7328.

Corresponding Author: email: basu@bu.edu; Tel.: +1 617 353 6728; fax: +1 617 353 5548.

1. Introduction

$\text{La}_x\text{Sr}_{1-x}\text{Co}_y\text{Fe}_{1-y}\text{O}_{3-\delta}$ (LSCF) has been widely used as the cathode material for solid oxide fuel cells (SOFCs) due to its outstanding mixed ionic-electronic conductivity [1], [2], [3] and [4], decent catalytic activity for oxygen reduction reaction [5] and [6] and excellent coefficient of thermal expansion (CTE) match with the electrolyte (typically yttria-stabilized zirconia (YSZ) and/or gadolinia-doped ceria (GDC)) [7], [8] and [9]. However, LSCF suffers from long-term stability issues when operated at SOFC working temperatures (typically at 800-1000 °C) [10], [11] and [12]. Segregation of Sr to the cathode surface and formation of secondary phases is one of the key degradation mechanisms in LSCF cathodes [10], [13], [14] and [15]. The formation of SrO and SrCO_3 even with trace amount of CO_2 present in the environment has been observed, and the kinetics of this segregation has been reported in the literature [14]. The composition and morphology of the surface phases is still not fully understood.

A number of characterization methods have been utilized to investigate the nature of the segregated Sr, including surface-sensitive x-ray and microscopy techniques. Total reflection x-ray fluorescence (TXRF) has also been used to depth profile the concentration of Sr in the near-surface region [14], [16] and [17]. X-ray photoelectron spectroscopy (XPS) has been widely used to study the bonding environment of surface Sr and to identify and quantify the surface precipitates in the macroscopic regime [14], [15], [18] and [19]. Electron microscopy and related spectroscopy techniques have been used to study the morphology of the Sr-rich surface particles and qualitatively examine their compositions [10].

The TXRF technique has been utilized in this study to examine the Sr segregation on the surface. TXRF is a surface-sensitive, non-destructive technique used for elemental analysis on the surface of materials, and is based on energy dispersive XRF spectroscopy. In this technique, the incident photon beam scans from a grazing incident angle below the critical angle towards increasing angles, while the detector collects the fluorescence signals. By measuring the integrated intensities of each X-ray emission line, which is proportional to their elemental concentrations, it is possible to depth profile the concentration of all the elements of interest. Thus, TXRF is the ideal technique to quantify the extent of Sr surface segregation.

X-ray photoelectron spectroscopy (XPS) is a powerful surface-sensitive quantitative spectroscopic technique that probes the electronic structure and the chemical and bonding environments at the surfaces of samples [20]. In this study, XPS with high incident photon energies, known as hard x-ray photoelectron spectroscopy (HAXPES), was used to study the chemistry and bonding environment of the surface of the sample before and after annealing. HAXPES offers significant advantages over soft x-ray XPS techniques in that it can overcome surface contamination issues and that it preserves the surface configurations. Higher incident photon energies used in HAXPES results in larger kinetic energy of photoelectrons and thus larger escape depth of photoelectrons, leading to improved signals without the need to heat the sample in vacuum, which is necessary for conventional soft x-ray measurements.

It is also essential to investigate the quantitative chemical composition of the Sr-rich surface precipitates to understand the nature of Sr surface segregation. This needs a technique that can quantify chemical compositions at high spatial resolution. The ideal technique for this purpose is scanning transmission electron microscopy (STEM) based energy dispersive x-ray

spectroscopy (EDS). A cross-sectional TEM specimen was prepared in an FEI Quanta 3D FEG focused ion beam (FIB) system* with an in-situ lift-out using Omniprobe micromanipulator*. This technique was chosen due to its excellent spatial resolution for a site-specific cross-sectional TEM specimen preparation [21]. The TEM specimen was extracted from a $\text{La}_{0.7}\text{Sr}_{0.3}\text{Co}_{0.2}\text{Fe}_{0.8}\text{O}_{3-\delta}$ (LSCF-7328) thin film, that had been annealed at 800 °C in a simulated anode exhaust gas environment containing CO_2 to mimic a possible scenario in SOFC operation, where a leakage happens at the anode side [22] and [23]. A high-resolution Tecnai Osiris TEM/STEM* with a four- quadrant windowless Super-X silicon-drift detector optimized for analytical work was used in this study.

2. Experimental

2.1 Thin film deposition.

(001)-oriented $\text{La}_{0.7}\text{Sr}_{0.3}\text{Co}_{0.2}\text{Fe}_{0.8}\text{O}_{3-\delta}$ thin films were deposited onto 10 mm × 10 mm × 0.5 mm lattice matched (110)- NdGaO_3 (NGO) single-crystal substrates by pulsed laser deposition (PLD). The films were deposited under 10 mTorr oxygen partial pressure with substrates kept at 550 °C. The PLD target was prepared by calcining a mixture of corresponding precursor powders that yield LSCF with 70% La, 30% Sr on A-site and 20% Co, 80% Fe on B-site (LSCF-7328). The powders were confirmed to be single phase using x-ray diffraction (XRD). The heteroepitaxy of (001) LSCF-7328 || (110) NGO was confirmed by XRD and the surface of the as-deposited film was characterized by a Bruker Dimension 3000 AFM*.

Sample processing.

A stainless steel chamber capable of being heated up to 1000 °C was used for annealing the LSCF-7328 sample. Before annealing, the chamber was first flushed with a mixture of gases consisting of 30% CO₂ – 21% O₂ – 49% N₂ for 15 min to yield 0.3 atm p_{CO_2} , 0.21 atm p_{O_2} and 0.49 atm p_{N_2} of a total of 1 atm in the chamber. The sample was heated to 800 °C from room temperature in 40 minutes and then kept heated at 800 °C for 9 hours. After annealing, the sample was quenched down to room temperature in the chamber, by abruptly turning off the power supply of heating element of chamber. The flow rate of the gas mixture was kept at 1L·min⁻¹ throughout the experiment. The surface morphology of post-annealed sample was characterized by both Bruker Dimension 3000 AFM* and Zeiss Supra 55VP field emission SEM*.

2.2 Total reflection X-ray fluorescence (TXRF)

Synchrotron-based TXRF measurements were carried out at beamline X23A2 at the National Synchrotron Light Source-I (NSLS-I) at Brookhaven National Laboratory (BNL). The X23A2 beamline provides photons with energy ranges from 4.9 to 30 keV with a resolution of 2×10^{-4} ($\Delta E/E$). The photon flux was calibrated at 10^{10} photons/second with monochromator bandpass at 10 keV, 100 mA and 2.5 GeV. The spot size of the beam was set at 25 mm (H) × 1 mm (W). The beamline is also equipped with a Vortex four-element detector* with a resolution of approximately 220 eV at 6 keV [24]. TXRF experiments were carried out in the radiation hutch. A Huber goniometer was mounted onto the sample translation stage to vary the incident photon beam with respect to the surface of the sample. For a photon energy of 16,305 eV (which is 200 eV above Sr K-edge), the critical angle for LSCF is about 0.17°.

The X-ray spectrometer collects X-ray signals and generates the corresponding energy dispersive spectra. The elements of interest are 'windowed' by capturing their corresponding fluorescence lines with the optimal FWHMs and peak positions to maximize the counts while minimizing overlap with other lines. During TXRF experiments, the fluorescence signal of each element of interest within the sample can be counted individually as a function of incident angle of the X-ray beam, to obtain the concentration depth profiles of all the constituents.

2.3 Hard X-ray Photoelectron Spectroscopy (HAXPES).

Synchrotron-based HAXPES measurements were carried out at beamline X24A at NSLS-I at BNL. The X24A beamline provides multiple diffraction gratings and the energy of photons ranges from 1.8 to 8.2 keV. The flux was $\sim 10^{12}$ photons/second and the spot size of the beam was ~ 1 mm in diameter. X24A beamline is UHV compatible and shares ring vacuum. HAXPES measurements were carried out on the LSCF-7328 sample both before and after annealing, with a monochromatic incident photon energy of 3000 eV. The incident beam was set at 5 degrees relative to the surface of sample. The sample was kept in ultra-high vacuum (UHV) with chamber pressure less than 10^{-9} torr. Binding energies (BE) were calibrated using the Ag 3d (Ag $3d_{5/2}$ =368.27 eV) measured from a silver foil in electrical contact with the sample surface. Peak fitting was carried out using the XPSPeak peak fitting software package [25], using a procedure reported by van der Heide [26]. A Shirley background was utilized and a Voigt peak shape was assumed. The Sr 3d is a doublet due to spin-orbit splitting [27]. The Sr 3d doublet separation was set at 1.7 eV and area ratio ($3d_{5/2} : 3d_{3/2}$) was set at 1 : 0.66. The full width at half maximum (FWHM) values of Sr 3d peaks were set at 1 eV and 1.3 eV for bulk-bound and surface-bound Sr atoms, respectively.

2.4 TEM cross-section specimen preparation.

TEM specimens were made by in-situ lift-out in FIB. Figure 1 shows the details of the process steps. A layer of carbon of ~ 150 nm in thickness was first deposited onto the region of interest and a ~ 3.5 μm thick layer of Pt was then deposited on the carbon layer to protect the region of interest from damage by the Ga beam during the subsequent ion-milling processes (Figure 1b). The specimen was then cut out from the bulk, in-situ lifted-out with Omniprobe manipulator and transferred onto a TEM half grid made of molybdenum (Figure 1c). The specimen was then thinned down in FIB to about 200 nm thickness for TEM/STEM analysis, as shown in Figure 1d. The TEM specimen was then loaded onto a low background TEM holder optimized for analytical work in STEM and plasma cleaned with low energy ions in a Fischione Model 920 plasma cleaner* before loading into the TEM.

Figure 1. Process of a site-specific TEM cross-section specimen preparation using FIB. (a) Area of interest with surface precipitates. (b) Deposited Pt layer protecting the surface precipitates and film from damage by Ga ions during subsequent milling in FIB. (c) Extracted cross-section specimen on the TEM grid before thinning. (d) Top view of FIB thinned sample ready for TEM analysis.

2.5 TEM/STEM imaging and analysis.

Detailed microstructure characterization was carried out in an FEI Tecnai Osiris S/TEM* operating at 200 keV. The chemical composition and elemental mapping analysis of the region of interest were performed in a STEM mode with EDS using Super-X detector*. The EDS data and spectra were collected and analyzed using Esprit software from Bruker*. For quantification of the EDS spectra, the x-ray emission lines were chosen to avoid peak overlaps from different elements. X-ray emission lines from the Pt layer, from Cu (coming from the clip used to mount the sample in the TEM holder) and from Mo (coming from the TEM half-grid) were used only for deconvolution during quantification (Table 1).

3. Results and Discussion

The sample surface of LSCF-7328 was characterized using AFM both before and after annealing. Figure 2a shows an atomically smooth surface with an RMS roughness of 0.16 nm. Figure 2b is a representative three-dimensional AFM image of the post-annealed sample surface. Figure 2c is a low magnification SEM image showing surface morphology of the post-annealed LSCF-7328 sample. The images show that micron sized secondary phases are formed after annealing, in shapes of triangles, polygons and bars that were ~100 nm in height. Also, the surface of LSCF-7328 is roughened after annealing (Figure 2b and c).

Figure 2. Three-dimensional AFM images of a) atomically smooth as-deposited and b) post-annealed sample surface of LSCF-7328 with large precipitates and c) SEM image of sample surface of post-annealed LSCF-7328 showing formation of surface precipitates.

Figure 3 shows the processed data from TXRF measurements for LSCF-7328, plotted as $\text{Sr}/(\text{Sr}+\text{La})$ ratio versus the X-ray incident angle. The data processing procedures can be found elsewhere [14]. The profiles include measurements taken both before annealing (as-deposited) and after annealing (post-annealed), represented by blue and red dashed lines, respectively. Starting from the right of the critical angle position marked by the black dashed line in Figure 3, moving towards lower angles to the left gives the profile of $\text{Sr}/(\text{Sr}+\text{La})$ ratio going from bulk towards the surface of thin film. The Sr surface segregation as a result of annealing is seen by comparing the as-deposited and post-annealed profiles. Figure 3 shows that Sr segregates to the surface of LSCF thin films after annealing, that the $\text{Sr}/(\text{Sr}+\text{La})$ ratios increases and exceeds the bulk value in the surface region. It is interesting to note that there is some Sr deficiency at the top surface of the film in the as-deposited LSCF-7328 sample (Figure 3). It is speculated that

this is due to experimental issues related to TXRF measurements at very low incidence angles where the signals are very low, as opposed to a real Sr-depletion in the as-deposited films. Nevertheless, a comparison of profiles, and the changes between the TXRF plots between the as-deposited and annealed samples remain valid and clearly point to Sr enrichment at the sample surface on annealing.

Figure 3. Processed TXRF data for LSCF-7328 before and after annealing, plotted as Sr/(Sr+La) ratio versus X-ray beam incident angle. At critical angle, the penetration depth of X-ray beam is about 10 nm.

Figure 4 shows the Sr 3d core level spectra of as-deposited and post-annealed LSCF-7328 and corresponding peak fittings, obtained from HAXPES results. The spectra are fitted into a bulk-bound doublet (lower BEs with Sr 3d_{5/2}=131.7 eV) and two surface-bound doublets (higher BEs) of surface SrO (Sr 3d_{5/2}=133.0 eV) and surface SrCO₃ (Sr 3d_{5/2}=133.9 eV) [26]. The surface SrO

and SrCO_3 contributions in the as-deposited sample are attributed to reactions occurring during film growth. The fractional areas of Sr components are tabulated in Table 2. The surface Sr components increase and the bulk Sr component decreases after annealing, indicating the formation of SrO and SrCO_3 on the sample surface. Also, surface SrCO_3 increases significantly compared to surface SrO , resulting in a larger proportion of SrCO_3 detected on the surface of post-annealed LSCF-7328 sample (Table 2).

Figure 4. HAXPES Sr 3d spectra of LSCF-7328 sample before and after annealing. The spectra were deconvoluted into a combination of bulk perovskite (Sr^{2+} in LSCF lattice), surface SrO and surface SrCO_3 phases.

Figure 5 shows a STEM high-angle annular dark-field (HAADF) image of the FIB-prepared TEM specimen, revealing the cross section of a surface precipitate with different layers marked. The image shows that the thickness of LSCF-7328 film is ~ 220 nm. Above it there is a precipitate with thickness of ~ 117 nm and length of ~ 650 nm.

Figure 5. A STEM HAADF image of the cross-section specimen revealing one elongated precipitate on surface of the film with different regions marked: (1) Pt protective layer, (2) carbon layer, (3) the elongated precipitate, (4) LSCF-7328 thin film and (5) NGO substrate. The two sets of dashed lines show the areas where EDS line scans were performed and the black arrows point to the film/carbon and precipitate/carbon interfaces, respectively.

The quantitative elemental distribution of the region was investigated by analyzing EDS spectra collected in STEM mode from the regions shown in the HAADF STEM image (Figure 6a). Figure 6b-i show the quantitative EDS mapping results of La, Sr, Co, Fe, O, C, Nd and Ga, respectively,

with colors representing different atomic percentage. The color scale has been adjusted for La, Sr, Co and Fe such that the 0-100% scale corresponds to 0-20% atomic percentage, otherwise their mapping results would appear much darker due to their relatively low concentration compared with other existing elements in the specimen. The carbon layer, precipitate, LSCF thin film and NGO substrate can be easily distinguished from the EDS maps.

Figure 6. (a) A STEM HAADF image of the precipitate region. Quantitative elemental maps (in atomic percentage represented by colors) for b) La, c) Sr, d) Co, e) Fe, f) O, g) C, h) Nd, and i) Ga acquired from the same region as (a) using STEM-based EDS mapping. The black spot on the precipitate is a result of beam damage from accidental exposure in a spot mode.

The mapping results (Figure 6c and f) show that the precipitate region is rich in Sr and O, indicating the presence of a Sr-O compound. EDS quantification analyses were conducted at locations 3 to 5 marked in Figure 5 and results are summarized in Table 3. The EDS quantification at location 3 within the precipitate region shows a roughly 1:1 ratio of Sr to O in atomic percentage (Table 3), indicating the Sr-O compound is SrO, which agrees with our previous HAXPES results from an LSCF-6428 sample [14]. The EDS quantification results at locations 4 and 5 in Figure 5 show that the measured compositions of LSCF thin film and substrate agreed fairly well with the intended stoichiometry, as shown by the columns listing the percentage deviation of the measured values from the theoretical values in Table 3. In addition, Sr mapping result (Figure 6c) shows that there is a slight Sr depletion within the LSCF thin film layer at two edges near the interface of precipitate/LSCF thin film, indicating that the Sr contributing to SrO in the precipitate might be diffused from the LSCF lattice in the subsurface region. Similar results have been reported by Oh et al., where they have observed a decrease of Sr intensity within the subsurface region below a Sr- and O- enriched surface precipitate from a dense LSCF-6428 sample [10]. They explained the formation of SrO by a two-step mechanism involving the formation of oxygen vacancies and the subsequent precipitation of enriched Sr.

Interestingly, the triangular shaped features adjacent to the SrO precipitates due to surface roughening was found to be rich in Co (Figure 6d), indicating the possible formation of Co-rich phases. This is not likely to be elemental Co due to lack of a strong reducing agent needed to reduce Co cations (2+, 3+ or 4+) into elemental Co. It is not likely to be part of LSCF lattice either due to the absence of La, Sr and Fe in the region. So the 'surface roughness' might be

related to Co-rich oxide or carbonate. The low concentration of O indicated by O mapping (Figure 6f) within the Co-rich 'surface roughness' region is not surprising, because it is known that EDS is not optimized for quantification of light elements ($Z < 8$) due to their low x-ray emission energies, especially from a small region [28]. Both B-site Co migration and related phase formation have been reported previously [16] and [29]. Fuoss et al. showed that in LSCF-6428, B-site Co segregates uniformly to the sample surface at elevated temperatures indicating a dynamic nature of Co migration in LSCF under certain SOFC working conditions [16]. Similarly, Lai et al. investigated LSCF thin film exposed to air containing H_2O and CO_2 under SOFC operating conditions by x-ray spectroscopy techniques [29]. They observed a new Co-containing phase that was presumed to be Co_3O_4 resulting from the decomposition of $CoCO_3$.

The HAXPES results also indicate the presence of $SrCO_3$ on the post-annealed sample surface (Table 2). The carbon mapping result does show significant carbon at the surface region of the precipitate (Figure 6g). However, this can also be simply ascribed to the beam broadening effect from the deposited C layer during FIB-based sample preparation.

In order to eliminate the effects of beam broadening, STEM-based EDS line scans were performed in two regions. Figure 5 marks the regions over which EDS analyses were carried out as rectangles of 140 nm width perpendicular to direction of the line scans. The blue rectangle across the precipitate region, marked by arrow A in Figure 5, is perpendicular to the interface of precipitate/carbon layer, while the red rectangle across a non-precipitate region, marked by arrow B in Figure 5 is perpendicular to the interface of film/carbon layer. To minimize the statistical error, the data points contributing to the carbon profiles in dashed lines in Figure 7 were obtained by averaging the atomic percentage of carbon in every pixel on the line

segments perpendicular to the direction of arrows within the dashed boxes (i.e., over a width of 140 nm). This results in two different carbon line profiles. The carbon profile across the non-precipitate region was then shifted along the x-axis (Figure 7) such that the point on the carbon profile of arrow B representing the interface of LSCF-7328 film/carbon is aligned with that of arrow A representing the precipitate/carbon interface (black arrows in Figure 5), resulting in the red and blue dashed lines in Figure 7, respectively. The exact point of the interface is determined using the following method. Going in the direction towards the film surface, there exists a point on each of the line scans, beyond which the atomic percent of carbon of the two profiles are equal (so that the subtraction of the two profiles equals zero). This point is considered to be the location of the interfaces between carbon/film (location away from precipitate, i.e., scan B in Fig. 5) and carbon/precipitate (location of precipitate, i.e. scan A in Fig. 5). Therefore, lining up this point in each profile also spatially lines up the two interfaces. The distance between neighboring data points in both scans is 1.85 nm. Thus, the error in locating the precipitate/carbon interface (in the x-direction in Fig. 7) is ± 1.85 nm. The subtraction of shifted line B from line A gives the actual carbon profile in the precipitate, free of beam broadening effects, and is shown by the solid black line in Figure 7. For easier interpretation of data, the profiles are overlaid with the STEM HAADF image of the precipitate region where the line scan was conducted. Consequently, the enrichment of carbon at the outer surface of precipitate is confirmed, indicating the presence of SrCO_3 in the outer layer of the precipitate in addition to SrO as shown in the schematic in Figure 8. The EDS analysis shows that the volume of SrO is more than that of SrCO_3 in contrast to the HAXPES results. This is because the photoelectron escape depth is calculated to be less than 10 nm at 3000 eV incident photon

energy for LSCF-7328, implying that the HAXPES is referentially representing the outer layer of the precipitate, which is SrCO_3 . The mechanism of formation of SrCO_3 has been discussed elsewhere [14].

Since SrO and SrCO_3 are insulating phases, it is expected that the formation of these surface phases will degrade electrochemical performance by reducing the effective surface area over which the oxygen reduction reaction (ORR) can occur, as well as by increasing the area specific resistance (ASR) of the cathode. With the formation of Co-rich surface phases, the composition at the remaining LSCF at the surface is going towards lanthanum doped strontium ferrite (LSF). The electrochemical performance of LSF has been reported to be inferior to LSCF, despite the fact that LSF is thermodynamically more stable than LSCF [30]. Therefore, it is speculated that the observed formation of Co-rich phases at the cathode surface will degrade the electrochemical performance of the cathode.

Figure 7. Carbon profiles obtained from two EDS line scans performed across a precipitate (blue dashed line) and across a film/carbon interface without a precipitate (red dashed line) as indicated in Figure 5. The black solid line represents the actual carbon profile in the precipitate obtained by subtracting the red line from the blue line. The x-axis in this plot is perpendicular to the precipitate/carbon interface.

Figure 8. Schematic of precipitate formation with SrO and SrCO₃ on the surface of LSCF-7328 after annealing.

4. Conclusions

The Sr surface segregation phenomenon on LSCF-7328 was observed using TXRF technique and the chemical composition of surface precipitates on LSCF-7328 film was investigated and quantified using HAXPES and STEM-based EDS. Upon annealing at 800 °C under atmospheric pressure consisting of 0.3 atm $p\text{CO}_2$, 0.21 atm $p\text{O}_2$ and 0.49 atm $p\text{N}_2$, the LSCF-7328 film surface develops large precipitates of various shapes as well as ‘surface roughness’ at a smaller scale. The precipitates were shown to be SrO with a capping layer of SrCO₃ through a combination of EDS quantitative mapping and line scans over the cross-section of the precipitate region, including the removal of the beam broadening effects. The ‘surface roughness’ on LSCF-7328 film was found to be due to Co-rich phases. To the best of our knowledge, this is the first observation of Co-rich surface phases in LSCF by analytical electron microscopy. The formation

of surface phases is expected to affect the electrochemical performance of the cathode adversely.

Acknowledgements

This work is supported through the DOE SECA program under Grant DEFC2612FE0009656. A portion of the research was performed using EMSL, a DOE Office of Science User Facility sponsored by the Office of Biological and Environmental Research and located at Pacific Northwest National Laboratory. Use of the National Synchrotron Light Source, Brookhaven National Laboratory, was supported by the U.S. Department of Energy, Office of Science, Office of Basic Energy Sciences, under Contract No. DE-AC02-98CH10886. The authors acknowledge the use of the FIB/TEM Facility in the Photonics Center of Boston University. The authors would like to acknowledge the contribution of Mr. Barry Karlin at NIST.

Disclaimer

* The inclusion of company names is for completeness and does not represent an endorsement by the National Institute of Standards and Technology.

References

- [1] Y. Leng, S. Chan, Q. Liu, Development of LSCF–GDC composite cathodes for low-temperature solid oxide fuel cells with thin film GDC electrolyte, *Int. J. Hydrogen Energy*. 33 (2008) 3808–3817.
- [2] J.A. Lane, S.J. Benson, D. Waller, J.A. Kilner, Oxygen transport in $\text{La}_{0.6}\text{Sr}_{0.4}\text{Co}_{0.2}\text{Fe}_{0.8}\text{O}_{3-\delta}$, *Solid State Ionics*. 121 (1999) 201–208.
- [3] B. Steele, Properties of $\text{La}_{0.6}\text{Sr}_{0.4}\text{Co}_{0.2}\text{Fe}_{0.8}\text{O}_{3-x}$ (LSCF) double layer cathodes on gadolinium-doped cerium oxide (CGO) electrolytes II. Role of oxygen exchange and diffusion, *Solid State Ionics*. 106 (1998) 255–261.
- [4] B.T. Dalslet, M. Sjøgaard, P.V. Hendriksen, Defect chemistry and oxygen transport of $(\text{La}_{0.6}\text{Sr}_{0.4-x}\text{M}_x)_{0.99}\text{Co}_{0.2}\text{Fe}_{0.8}\text{O}_{3-\delta}$, $\text{M} = \text{Ca}$ ($x = 0.05, 0.1$), Ba ($x = 0.1, 0.2$), Part II: Oxygen transport, *Solid State Ionics*. 180 (2009) 1050–1060.
- [5] S.J. Skinner, Recent advances in Perovskite-type materials for solid oxide fuel cell cathodes, *Int. J. Inorg. Mater.* 3 (2001) 113–121.
- [6] C.C. Kan, E.D. Wachsman, Identifying Drivers of Catalytic Activity Through Systematic Surface Modification of Cathode Materials, *J. Electrochem. Soc.* 156 (2009) B695–B702.
- [7] H. Ullmann, N. Trofimenko, F. Tietz, D. Stöver, A. Ahmad-Khanlou, Correlation between thermal expansion and oxide ion transport in mixed conducting perovskite-type oxides for SOFC cathodes, *Solid State Ionics*. 138 (2000) 79–90.
- [8] A. Mai, V.A.C. Haanappel, S. Uhlenbruck, F. Tietz, Ferrite-based perovskites as cathode materials for anode- supported solid oxide fuel cells Part I . Variation of composition, *Solid State Ionics*. 176 (2008) 1–14.
- [9] A.O. Guimarães, A.M. Mansanares, V.F. Guimarães, H.R. Paes, H. Vargas, Assessment of the thermal expansion mismatch in lanthanum strontium cobalt ferrite-yttria stabilized zirconia two-layers systems using photoacoustic methodology, *Appl. Phys. Lett.* 102 (2013) 131910.
- [10] D. Oh, D. Gostovic, E.D. Wachsman, Mechanism of $\text{La}_{0.6}\text{Sr}_{0.4}\text{Co}_{0.2}\text{Fe}_{0.8}\text{O}_3$ cathode degradation, *J. Mater. Res.* 27 (2012) 1992–1999.
- [11] S.P. Simner, M.D. Anderson, M.H. Engelhard, J.W. Stevenson, Degradation Mechanisms of La-Sr-Co-Fe-O_3 SOFC Cathodes, *Electrochem. Solid-State Lett.* 9 (2006) A478–A481.
- [12] A. Mai, M. Becker, W. Assenmacher, F. Tietz, D. Hathiramani, E. Iverstiffe, D. Stover, W. Mader, Time-dependent performance of mixed-conducting SOFC cathodes, *Solid State Ionics*. 177 (2006) 1965–1968.
- [13] M. Finsterbusch, A. Lussier, J.A. Schaefer, Y.U. Idzerda, Electrochemically driven cation segregation in the mixed conductor $\text{La}_{0.6}\text{Sr}_{0.4}\text{Co}_{0.2}\text{Fe}_{0.8}\text{O}_{3-\delta}$, *Solid State Ionics*. 212 (2012) 77–80.

- [14] Y. Yu, H. Luo, D. Cetin, X. Lin, K.F. Ludwig, U.B. Pal, S. Gopalan, S.N. Basu, Effect of atmospheric CO₂ on surface segregation and phase formation in La_{0.6}Sr_{0.4}Co_{0.2}Fe_{0.8}O_{3-δ} thin films, *Appl. Surf. Sci.* 323 (2014) 71–77.
- [15] W. Jung, H.L. Tuller, Investigation of surface Sr segregation in model thin film solid oxide fuel cell perovskite electrodes, *Energy Environ. Sci.* 5 (2012) 5370.
- [16] P. Fuoss, K.-C. Chang, H. You, In situ X-ray studies of film cathodes for solid oxide fuel cells, *J. Electron Spectros. Relat. Phenomena.* 190 (2013) 75–83.
- [17] T.T. Fister, D.D. Fong, J.A. Eastman, P.M. Baldo, M.J. Highland, P.H. Fuoss, K.R. Balasubramaniam, J.C. Meador, P.A. Salvador, In situ characterization of strontium surface segregation in epitaxial La_{0.7}Sr_{0.3}MnO₃ thin films as a function of oxygen partial pressure, *Appl. Phys. Lett.* 93 (2008) 151904.
- [18] M. Finsterbusch, A. Lussier, J.A. Schaefer, Y.U. Idzerda, Electrochemically driven cation segregation in the mixed conductor La_{0.6}Sr_{0.4}Co_{0.2}Fe_{0.8}O_{3-δ}, *Solid State Ionics.* 212 (2012) 77–80.
- [19] E.J. Crumlin, E. Mutoro, Z. Liu, M.E. Grass, M.D. Biegalski, Y.-L. Lee, D. Morgan, H.M. Christen, H. Bluhm, Y. Shao-Horn, Surface strontium enrichment on highly active perovskites for oxygen electrocatalysis in solid oxide fuel cells, *Energy Environ. Sci.* 5 (2012) 6081.
- [20] W.E. Swartz, X-ray photoelectron spectroscopy, *Anal. Chem.* 45 (1973) 788A–800a.
- [21] L. Giannuzzi, *Introduction to Focused Ion Beams: Instrumentation, Theory, Techniques and Practice*, Springer Science & Business Media, 2006.
- [22] M. Bram, S. Reckers, P. Drinovac, J. Mönch, R.W. Steinbrech, H.P. Buchkremer, D. Stöver, Deformation behavior and leakage tests of alternate sealing materials for SOFC stacks, *J. Power Sources.* 138 (2004) 111–119.
- [23] Y. Tanaka, A. Momma, K. Sato, T. Kato, M. Williams, N. Garland, Improvement of Electrical Efficiency of Solid Oxide Fuel Cells by Anode Gas Recycle, in: *ECS Trans.*, The Electrochemical Society, 2011: pp. 145–150.
- [24] J.C. Woicik, B. Ravel, D.A. Fischer, W.J. Newburgh, Performance of a four-element Si drift detector for X-ray absorption fine-structure spectroscopy: resolution, maximum count rate, and dead-time correction with incorporation into the ATHENA data analysis software., *J. Synchrotron Radiat.* 17 (2010) 409–13.
- [25] R. Kwok, XPS peak fitting program for WIN95/98 XPSPEAK version 4.1, (2000).
- [26] P.A.W. van der Heide, Systematic x-ray photoelectron spectroscopic study of La_{1-x}Sr_x-based perovskite-type oxides, *Surf. Interface Anal.* 33 (2002) 414–425.
- [27] A. Thompson, D. Attwood, E. Gullikson, *X-Ray Data Booklet*, Lawrence Berkeley National Laboratory, (2009).

- [28] D.B. Williams, C.B. Carter, Transmission Electron Microscopy, Springer US, Boston, MA, 2009.
- [29] S.Y. Lai, D. Ding, M. Liu, M. Liu, F.M. Alamgir, Operando and in situ X-ray spectroscopies of degradation in $\text{La}_{0.6}\text{Sr}_{0.4}\text{Co}_{0.2}\text{Fe}_{0.8}\text{O}_{3-\delta}$ thin film cathodes in fuel cells., ChemSusChem. 7 (2014) 3078–87.
- [30] C. Sun, R. Hui, J. Roller. Cathode materials for solid oxide fuel cells: a review. J Solid State Electrochem 14, no. 7 (2009): 1125-1144.
- [31] C. Wagner, NIST X-ray photoelectron spectroscopy database. (2000)
<http://srdata.nist.gov/xps/>

Tables

Table 1. X-ray emission lines used in EDS quantification. [31]

Element	Atomic No.	X-ray lines	Energy (eV)	Purpose
La	57	$L\alpha_1$	4.6510	Quantification
Sr	38	$K\alpha_1$	14.1650	
Co	27	$K\alpha_1$	6.9303	
Fe	26	$K\alpha_1$	6.4038	
O	8	$K\alpha_1$	0.5249	
C	6	$K\alpha_1$	0.2770	
Nd	60	$L\alpha_1$	5.2304	
Ga	31	$L\alpha_1$	1.0979	Deconvolution
Pt	78	$L\alpha_1$	9.4423	
Cu	29	$K\alpha_1$	8.0478	
Mo	42	$L\alpha_1$	2.2932	

Table 2. Fractional areas of Sr $3d_{5/2}$ peaks for bulk, surface SrO and SrCO₃ components. (unit: %)

	Bulk	Surface SrO	Surface SrCO ₃
As-deposited	79.8	9.4	10.8
Post-annealed	55.3	12.1	32.6

Table 3. EDS quantification results of regions indicated in Figure 5.

	Precipitate (position 3)			Film (position 4)			Substrate (position 5)		
	Measured (at %)	Theory (at %)	Deviation from theory (%)	Measured (at %)	Theory (at %)	Deviation from theory (%)	Measured (at %)	Theory (at %)	Deviation from theory (%)
La	0.9			13.5	14.0	-3.3	0.1	0.0	
Sr	45.7			5.7	6.0	-4.4	0.1	0.0	
Co	0.3			3.8	4.0	-6.1	0.0	0.0	N/A
Fe	1.0			15.4	16.0	-3.9	0.4	0.0	
O	47.8		N/A	57.9	60.0	-3.4	59.5	60.0	-0.9
C	2.8			2.2	0.0		2.0	0.0	N/A
Nd	0.5			0.8	0.0	N/A	19.0	20.0	-5.1
Ga	1.0			0.6	0.0		19.0	20.0	-5.0